

KV-27XSD/KV-27XSTA/KV-27XSC/27XSTC

RM-635

RM-634

RM-635


AEP Model

KV-27XSC

Chassis No. SCC-774E-A

KV-27XSTC


Chassis No. SCC-774D-A



RX-2 CHASSIS

August, 1986


CIRCUIT BOARDS LOCATION






SPECIFICATIONS

Television system	CCIR TV standards (system B, G and H)
Colour system	PAL
Zeiton system	Two carrier system
Channel coverage	VHF channels E2-S20 UHF channels E21-E68
Programming system	30 programmes Automatic programming digital tuning
Picture tube	Approx. 68 cm (27 inches), approx. 64 cm screen measured diagonally 114-degree deflection Trinitron system
Aerial	75-ohm standard aerial socket (DIN 45325/IEC 169-2)
Audio output	10 W + 10 W (music power)
Input/output	21-pin connector in accordance with the requirements of CENELEC standard
Outputs	Audio output connector (5-pin DIN) Recording output: 1 mV rms/kilohm Line output: variable, 0-2 V rms (max.) impedance less than 1 kilohm External speaker terminals (2-pin DIN) For 8 to 16 ohm speakers Headphones jack (stereo phone jack)
Power requirements	220-240 V ac, 50 Hz
Power consumption	120Wh
Dimensions	Approx. 800 x 543 x 475 mm (w/h/d)
Weight	Approx. 52kg
Accessory supplied	Remote Commander RM-635
Optional accessory	OPK-202 SECAM adaptor OPK-303 teletext adaptor (KV-27XSC ONLY)


KV27XS-C/TC/D/XSTA
427









(KV27XSTA only)




(KV27XSTA only)






SCM

[SCM-KILLER, Y DRIVE, PAL-SECAM TRANSCODER] (KV27XSD only)




(KV27XSD only)



CONNECTOR	DIODE	RESISTOR
SCM-1 C-1	D1351 C-3	R1351 B-2 R1352 B-2 R1353 B-2 R1354 B-2 R1355 C-2 R1356 A-2 R1357 B-3 R1361 B-3 R1364 B-4 R1365 B-4
CAPACITOR	IC	
C1351 B-2 C1352 B-3 C1353 B-2 C1354 B-2 C1355 B-1 C1356 B-2 C1357 B-1 C1358 B-1 C1359 C-1 C1360 C-1	IC1351 B-1	
C1361 B-4 C1362 A-3 C1363 A-4 C1364 A-3 C1366 A-1 C1367 A-1 C1368 A-1 C1369 A-2 C1370 A-2 C1371 A-2	COIL	
C1372 A-2 C1373 B-2 C1374 C-4 C1375 A-1 C1376 C-3 C1378	L1351 A-2 L1352 A-4 L1353 A-1 L1354 A-2	
	TRANSISTOR	
	Q1351 C-2 Q1352 C-3 Q1354 B-4 Q1356 A-3 Q1357 B-3 Q1359 B-2 Q1360 C-3	R1367 C-3 R1368 B-3 R1371 B-3 R1372 A-3 R1373 A-1 R1374 A-1 R1375 A-3 R1380 B-3 R1382 A-3 R1383 A-3 R1384 B-2 R1385 B-3 R1386 C-3 R1387 B-3 R1388 B-3 R1389 B-1 R1390 A-2
		VARIABLE RESISTOR
		RV1351 A-2


SCM

KV27XS-C/TC/D/XSTA
435



F

[REG OUT]






F

CAPACITOR		D652	A-3	R612	D-4
C601	G-1	D653	A-3	R613	C-5
C602	G-4	D654	B-5	R614	D-5
C603	H-6	D654A	B-5		
C604	G-6	D655	B-5	R615	D-5
C605	F-5	D655A	B-5	R616	D-2
C606	G-6	D656	B-5	R621	D-2
C607	F-5	D657	B-3	R622	E-2
C608	G-5	D658	B-6	R623	D-2
C609	F-4	D659	C-6	R624	E-2
C610	F-6	D660	A-4	R625	E-2
		D661	A-5	R626	E-2
				R627	F-2
C611	E-1	D663	B-2	R628	F-2
C612	E-1	D664	C-2		
C613	E-1	CONNECTOR		R629	E-2
C614	E-2			R630	E-4
C615	E-2	F1 H-1 F2 H-2 F3 H-4 F4 A-2 F5 C-6 F6 A-3 F7 A-5		R631	E-5
C616	E-2			R632	D-3
C617	F-2			R633	C-1
C618	F-2			R634	D-1
C619	F-1			R635	D-1
C620	D-2			R636	E-1
				R637	E-3
C621	E-5		R638	D-2	
C622	D-6	FUSE		R639	E-3
C623	C-1			R640	G-2
C624	C-1	F601 G-1		R641	H-2
C625	D-1			R651	B-3
C626	D-1			R652	A-6
C627	E-2			R653	B-6
C628	F-1	IC		R654	A-2
C632	C-4			R657	A-2
C633	G-2			R659	B-4
				R660	B-5
C634	D-2	IC601	E-2	R662	C-1
C651	A-1	IC602	C-2	R663	B-1
C652	A-2	IC651	B-2	R664	B-1
C653	A-3	COIL		R665	B-1
C654	C-5			R666	B-2
C655	C-5			R667	B-2
C656	B-1			R668	A-3
C658	B-5	L601	F-3	R669	B-1
C659	C-4	L651	B-2	R670	A-1
C660	A-4	L652	A-4		
C661	B-6	TRANSISTOR		VARIABLE RESISTOR	
C662	C-1				
C663	B-1	Q601	E-2	RV651	B-1
C664	C-2	Q602	E-3	RV652	C-1
C666	C-6	Q603	D-1		
C667	B-1	Q604	D-1	TRANSFORMER	
C668	A-3	Q651	A-5		
		Q652	B-6		
DIODE		RESISTOR		T601	G-3
				T602	H-5
D601	F-5	R601	F-3	T603	E-3
D602	C-2	R602	G-4	T605	C-3
D603	E-2	R603	G-3	THERMISTOR	
D604	E-2	R604	H-6		
D605	C-5	R605	F-1	TH601	E-2
D606	C-1	R606	F-1	TH651	A-1
D607	D-4	R608	D-1	THP601	G-3
D608	D-6	R609	D-2		
D609	E-5	R611	E-1		
D651	A-1				

[BAND SW, QUASI, ID,
SIF, VIF, AFT, MATRIX]


[PIN CTRL, Y BOW]





A

CONNECTOR		C135 D-2 C136 D-3 C137 B-2 C138 B-2 C139 C-2 C140 C-2 C141 D-2 C142 D-5 C143 B-5 C144 C-5	C180 D-6 C181 C-6 C182 D-7 C183 D-6 C184 D-5 C186 D-7 C188 C-3 C189 D-1	COIL	RESISTOR	R152 C-6 R153 A-6 R154 C-7	SAW FILTER
A1 B-8 A2 B-8 A3 A-1				L101 B-5 L102 B-4 L103 B-4 L104 C-4 L105 D-5 L106 D-2 L107 D-3 L109 D-5 L110 D-2 L111 D-4 L113 C-1	R101 B-1 R102 B-1 R105 D-3 R106 D-3 R107 C-2 R108 D-1 R109 D-1 R110 D-1 R111 B-4 R112 B-4	R155 B-8 R156 C-6 R157 C-7 R158 C-7 R159 D-7 R160 D-7 R161 C-8 R162 D-8 R166 A-8 R167 A-8	SWF101B3
CAPACITOR			FILTER				TUNER
C102 A-1 C104 B-1 C105 B-1 C106 A-2 C107 B-2 C108 C-1 C109 D-2 C110 D-1 C111 D-1 C112 B-5	C145 B-6 C146 B-7 C147 B-6 C148 B-6 C149 B-5 C150 C-4 C151 A-7 C152 A-7 C153 B-7 C154 A-7	CD151 A-6 CF101 C-4 CF102 D-5 CF151 A-6	DIODE	L114 A-1 L116 B-4 L117 B-6 L170 D-6 L171 D-6	R113 C-4 R114 C-4 R115 C-2 R116 B-3 R117 B-4 R118 D-5 R119 D-8 R120 D-3 R122 C-3 R125 C-4	R168 A-7 R172 D-7 R173 D-7 R174 D-7 R175 D-6 R176 D-6 R177 C-6 R178 D-7 R179 D-7 R180 D-6	TU101 A-3
C113 B-5 C114 B-4 C115 B-4 C116 B-4 C117 B-3 C118 C-4 C119 B-3 C120 C-4 C122 B-5 C123 C-5	C155 A-7 C156 B-7 C157 B-7 C158 C-7 C159 B-6 C160 B-7 C164 B-6 C165 C-6 C167 C-6 C168 C-7		TRANSISTOR	Q101 D-2 Q102 C-3 Q103 D-7 Q104 D-1 Q105 B-7 Q151 D-8 Q152 D-8 Q153 B-6 Q154 A-8 Q155 A-8	R126 D-4 R127 C-4 R129 C-1 R131 C-1 R132 A-1 R134 D-3 R135 C-3 R136 A-7 R137 C-1 R140 A-1	R181 D-6 R182 D-6 R183 C-8 R184 C-8 R185 A-6 R188 C-6 R191 C-8 R192 D-8 R193 D-2	
C124 D-5 C126 C-4 C127 C-4 C128 D-4 C129 C-4 C130 B-2 C131 C-3 C132 C-3 C133 D-3 C134 C-3	C169 C-6 C170 D-6 C171 D-6 C172 C-6 C173 C-7 C174 C-7 C175 D-7 C176 C-8 C177 D-8 C179 D-7	D101 C-1 D102 A-7 D103 B-1 D104 C-5 D105 B-7 D151 A-6 D152 A-8 D153 A-8 D154 B-8 D170 C-6 D171 D-7	IC	Q156 A-8 Q157 A-8 Q158 B-8 Q172 D-6 Q173 C-5 Q174 C-6 Q175 C-8	R141 B-6 R142 A-7 R143 A-7 R144 B-1 R145 B-6 R146 C-1 R151 A-6	VARIABLE RESISTOR	RV101 C-3 RV151 C-7
		IC101 C-2 IC102 C-4 IC103 B-2 IC151 B-6 IC152 C-6					


[CCT, μ -PROCESSOR] KV-27XSTC ONLY


D

CAPACITOR	C133 A-10	C134 A-12	C135 A-11	C136 A-10	C137 A-11	C138 B-11	C139 A-12	C140 C-12	C141 C-12	C142 C-11	C143 D-11	C144 D-12	C145 D-12	C146 D-12	C147 C-11	C148 D-11	C149 C-10	C150 B-11	C151 A-4	C152 C-12	C153 B-9	C154 A-10	C155 D-13	C156 D-13	C157 E-13	C158 A-11	C159 C-13	C160 C-13	C161 C-12	C162 D-13	C163 D-12	C164 B-9	C165 B-13	C166 B-9	C167 I-12	C168 I-11	C169 I-11	C170 J-7	C171 J-7	C172 J-7	C173 J-6	C174 J-6	C175 J-6	C176 J-6	C177 J-6	C178 J-6	C179 J-6	C180 J-6	C181 J-6	C182 J-6	C183 J-6	C184 J-6	C185 J-6	C186 J-6	C187 J-6	C188 J-6	C189 J-6	C190 J-6	C191 J-6	C192 J-6	C193 J-6	C194 J-6	C195 J-6	C196 J-6	C197 J-6	C198 J-6	C199 J-6	C200 J-6	C201 J-6	C202 J-6	C203 J-6	C204 J-6	C205 J-6	C206 J-6	C207 J-6	C208 J-6	C209 J-6	C210 J-6	C211 J-6	C212 J-6	C213 J-6	C214 J-6	C215 J-6	C216 J-6	C217 J-6	C218 J-6	C219 J-6	C220 J-6	C221 J-6	C222 J-6	C223 J-6	C224 J-6	C225 J-6	C226 J-6	C227 J-6	C228 J-6	C229 J-6	C230 J-6	C231 J-6	C232 J-6	C233 J-6	C234 J-6	C235 J-6	C236 J-6	C237 J-6	C238 J-6	C239 J-6	C240 J-6	C241 J-6	C242 J-6	C243 J-6	C244 J-6	C245 J-6	C246 J-6	C247 J-6	C248 J-6	C249 J-6	C250 J-6	C251 J-6	C252 J-6	C253 J-6	C254 J-6	C255 J-6	C256 J-6	C257 J-6	C258 J-6	C259 J-6	C260 J-6	C261 J-6	C262 J-6	C263 J-6	C264 J-6	C265 J-6	C266 J-6	C267 J-6	C268 J-6	C269 J-6	C270 J-6	C271 J-6	C272 J-6	C273 J-6	C274 J-6	C275 J-6	C276 J-6	C277 J-6	C278 J-6	C279 J-6	C280 J-6	C281 J-6	C282 J-6	C283 J-6	C284 J-6	C285 J-6	C286 J-6	C287 J-6	C288 J-6	C289 J-6	C290 J-6	C291 J-6	C292 J-6	C293 J-6	C294 J-6	C295 J-6	C296 J-6	C297 J-6	C298 J-6	C299 J-6	C300 J-6	C301 J-6	C302 J-6	C303 J-6	C304 J-6	C305 J-6	C306 J-6	C307 J-6	C308 J-6	C309 J-6	C310 J-6	C311 J-6	C312 J-6
	C133 A-10	C134 A-12	C135 A-11	C136 A-10	C137 A-11	C138 B-11	C139 A-12	C140 C-12	C141 C-12	C142 C-11	C143 D-11	C144 D-12	C145 D-12	C146 D-12	C147 C-11	C148 D-11	C149 C-10	C150 B-11	C151 A-4	C152 C-12	C153 B-9	C154 A-10	C155 D-13	C156 D-13	C157 E-13	C158 A-11	C159 C-13	C160 C-13	C161 C-12	C162 D-13	C163 D-12	C164 B-9	C165 B-13	C166 B-9	C167 I-12	C168 I-11	C169 I-11	C170 J-7	C171 J-7	C172 J-7	C173 J-6	C174 J-6	C175 J-6	C176 J-6	C177 J-6	C178 J-6	C179 J-6	C180 J-6	C181 J-6	C182 J-6	C183 J-6	C184 J-6	C185 J-6	C186 J-6	C187 J-6	C188 J-6	C189 J-6	C190 J-6	C191 J-6	C192 J-6	C193 J-6	C194 J-6	C195 J-6	C196 J-6	C197 J-6	C198 J-6	C199 J-6	C200 J-6	C201 J-6	C202 J-6	C203 J-6	C204 J-6	C205 J-6	C206 J-6	C207 J-6	C208 J-6	C209 J-6	C210 J-6	C211 J-6	C212 J-6	C213 J-6	C214 J-6	C215 J-6	C216 J-6	C217 J-6	C218 J-6	C219 J-6	C220 J-6	C221 J-6	C222 J-6	C223 J-6	C224 J-6	C225 J-6	C226 J-6	C227 J-6	C228 J-6	C229 J-6	C230 J-6	C231 J-6	C232 J-6	C233 J-6	C234 J-6	C235 J-6	C236 J-6	C237 J-6	C238 J-6	C239 J-6	C240 J-6	C241 J-6	C242 J-6	C243 J-6	C244 J-6	C245 J-6	C246 J-6	C247 J-6	C248 J-6	C249 J-6	C250 J-6	C251 J-6	C252 J-6	C253 J-6	C254 J-6	C255 J-6	C256 J-6	C257 J-6	C258 J-6	C259 J-6	C260 J-6	C261 J-6	C262 J-6	C263 J-6	C264 J-6	C265 J-6	C266 J-6	C267 J-6	C268 J-6	C269 J-6	C270 J-6	C271 J-6	C272 J-6	C273 J-6	C274 J-6	C275 J-6	C276 J-6	C277 J-6	C278 J-6	C279 J-6	C280 J-6	C281 J-6	C282 J-6	C283 J-6	C284 J-6	C285 J-6	C286 J-6	C287 J-6	C288 J-6	C289 J-6	C290 J-6	C291 J-6	C292 J-6	C293 J-6	C294 J-6	C295 J-6	C296 J-6	C297 J-6	C298 J-6	C299 J-6	C300 J-6	C301 J-6	C302 J-6	C303 J-6	C304 J-6	C305 J-6	C306 J-6	C307 J-6	C308 J-6	C309 J-6	C310 J-6	C311 J-6	C312 J-6
	C133 A-10	C134 A-12	C135 A-11	C136 A-10	C137 A-11	C138 B-11	C139 A-12	C140 C-12	C141 C-12	C142 C-11	C143 D-11	C144 D-12	C145 D-12	C146 D-12	C147 C-11	C148 D-11	C149 C-10	C150 B-11	C151 A-4	C152 C-12	C153 B-9	C154 A-10	C155 D-13	C156 D-13	C157 E-13	C158 A-11	C159 C-13	C160 C-13	C161 C-12	C162 D-13	C163 D-12	C164 B-9	C165 B-13	C166 B-9	C167 I-12	C168 I-11	C169 I-11	C170 J-7	C171 J-7	C172 J-7	C173 J-6	C174 J-6	C175 J-6	C176 J-6	C177 J-6	C178 J-6	C179 J-6	C180 J-6	C181 J-6	C182 J-6	C183 J-6	C184 J-6	C185 J-6	C186 J-6	C187 J-6	C188 J-6	C189 J-6	C190 J-6	C191 J-6	C192 J-6	C193 J-6	C194 J-6	C195 J-6	C196 J-6	C197 J-6	C198 J-6	C199 J-6	C200 J-6	C201 J-6	C202 J-6	C203 J-6	C204 J-6	C205 J-6	C206 J-6	C207 J-6	C208 J-6	C209 J-6	C210 J-6	C211 J-6	C212 J-6	C213 J-6	C214 J-6	C215 J-6	C216 J-6	C217 J-6	C218 J-6	C219 J-6	C220 J-6	C221 J-6	C222 J-6	C223 J-6	C224 J-6	C225 J-6	C226 J-6	C227 J-6	C228 J-6	C229 J-6	C230 J-6	C231 J-6	C232 J-6	C233 J-6	C234 J-6	C235 J-6	C236 J-6	C237 J-6	C238 J-6	C239 J-6	C240 J-6	C241 J-6	C242 J-6	C243 J-6	C244 J-6	C245 J-6	C246 J-6	C247 J-6	C248 J-6	C249 J-6	C250 J-6	C251 J-6	C252 J-6	C253 J-6	C254 J-6	C255 J-6	C256 J-6	C257 J-6	C258 J-6	C259 J-6	C260 J-6	C261 J-6	C262 J-6	C263 J-6	C264 J-6	C265 J-6	C266 J-6	C267 J-6	C268 J-6	C269 J-6	C270 J-6	C271 J-6	C272 J-6	C273 J-6	C274 J-6	C275 J-6	C276 J-6	C277 J-6	C278 J-6	C279 J-6	C280 J-6	C281 J-6	C282 J-6	C283 J-6	C284 J-6	C285 J-6	C286 J-6	C287 J-6	C288 J-6	C289 J-6	C290 J-6	C291 J-6	C292 J-6	C293 J-6	C294 J-6	C295 J-6	C296 J-6	C297 J-6	C298 J-6	C299 J-6	C300 J-6	C301 J-6	C302 J-6	C303 J-6	C304 J-6	C305 J-6	C306 J-6	C307 J-6	C308 J-6	C309 J-6	C310 J-6	C311 J-6	C312 J-6
	C133 A-10	C134 A-12	C135 A-11	C136 A-10	C137 A-11	C138 B-11	C139 A-12	C140 C-12	C141 C-12	C142 C-11	C143 D-11	C144 D-12	C145 D-12	C146 D-12	C147 C-11	C148 D-11	C149 C-10	C150 B-11	C151 A-4	C152 C-12	C153 B-9	C154 A-10	C155 D-13	C156 D-13	C157 E-13	C158 A-11	C159 C-13	C160 C-13	C161 C-12	C162 D-13	C163 D-12	C164 B-9	C165 B-13	C166 B-9	C167 I-12	C168 I-11	C169 I-11	C170 J-7	C171 J-7	C172 J-7	C173 J-6	C174 J-6	C175 J-6	C176 J-6	C177 J-6	C178 J-6	C179 J-6	C180 J-6	C181 J-6	C182 J-6	C183 J-6	C184 J-6	C185 J-6	C186 J-6	C187 J-6	C188 J-6	C189 J-6	C190 J-6	C191 J-6	C192 J-6	C193 J-6	C194 J-6	C195 J-6	C196 J-6	C197 J-6	C198 J-6	C199 J-6	C200 J-6	C201 J-6	C202 J-6	C203 J-6	C204 J-6	C205 J-6	C206 J-6	C207 J-6	C208 J-6	C209 J-6	C210 J-6	C211 J-6	C212 J-6	C213 J-6	C214 J-6	C215 J-6	C216 J-6	C217 J-6	C218 J-6	C219 J-6	C220 J-6	C221 J-6	C222 J-6	C223 J-6	C224 J-6	C225 J-6	C226 J-6	C227 J-6	C228 J-6	C229 J-6	C230 J-6	C231 J-6	C232 J-6	C233 J-6	C234 J-6	C235 J-6	C236 J-6	C237 J-6	C238 J-6	C239 J-6	C240 J-6	C241 J-6	C242 J-6	C243 J-6	C244 J-6	C245 J-6	C246 J-6	C247 J-6	C248 J-6	C249 J-6	C250 J-6	C251 J-6	C252 J-6	C253 J-6	C254 J-6	C255 J-6	C256 J-6	C257 J-6	C258 J-6	C259 J-6	C260 J-6	C261 J-6	C262 J-6	C263 J-6	C264 J-6	C265 J-6	C266 J-6	C267 J-6	C268 J-6	C269 J-6	C270 J-6	C271 J-6	C272 J-6	C273 J-6	C274 J-6	C275 J-6	C276 J-6	C277 J-6	C278 J-6	C279 J-6	C280 J-6	C281 J-6	C282 J-6	C283 J-6	C284 J-6	C285 J-6	C286 J-6	C287 J-6	C288 J-6	C289 J-6	C290 J-6	C291 J-6	C292 J-6	C293 J-6	C294 J-6	C295 J-6	C296 J-6	C297 J-6	C298 J-6	C299 J-6	C300 J-6	C301 J-6	C302 J-6	C303 J-6	C304 J-6	C305 J-6	C306 J-6	C307 J-6	C308 J-6	C309 J-6	C310 J-6	C311 J-6	C312 J-6
	C133 A-10	C134 A-12	C135 A-11	C136 A-10	C137 A-11	C138 B-11	C139 A-12	C140 C-12	C141 C-12	C142 C-11	C143 D-11	C144 D-12	C145 D-12	C146 D-12	C147 C-11	C148 D-11	C149 C-10	C150 B-11	C151 A-4	C152 C-12	C153 B-9	C154 A-10	C155 D-13	C156 D-13	C157 E-13	C158 A-11	C159 C-13	C160 C-13	C161 C-12	C162 D-13	C163 D-12	C164 B-9	C165 B-13	C166 B-9	C167 I-12	C168 I-11	C169 I-11	C170 J-7	C171 J-7	C172 J-7	C173 J-6	C174 J-6	C175 J-6	C176 J-6	C177 J-6	C178 J-6	C179 J-6	C180 J-6	C181 J-6	C182 J-6	C183 J-6	C184 J-6	C185 J-6	C186 J-6	C187 J-6	C188 J-6	C189 J-6	C190 J-6	C191 J-6	C192 J-6	C193 J-6	C194 J-6	C195 J-6	C196 J-6	C197 J-6	C198 J-6	C199 J-6	C200 J-6	C201 J-6	C202 J-6	C203 J-6	C204 J-6	C205 J-6	C206 J-6	C207 J-6	C208 J-6	C209 J-6	C210 J-6	C211 J-6	C212 J-6	C213 J-6	C214 J-6	C215 J-6	C216 J-6	C217 J-6	C218 J-6	C219 J-6	C220 J-6	C221 J-6	C222 J-6	C223 J-6	C224 J-6	C225 J-6	C226 J-6	C227 J-6	C228 J-6	C229 J-6	C230 J-6	C231 J-6	C232 J-6	C233 J-6	C234 J-6	C235 J-6	C236 J-6	C237 J-6	C238 J-6	C239 J-6	C240 J-6	C241 J-6	C242 J-6	C243 J-6	C244 J-6	C245 J-6	C246 J-6	C247 J-6	C248 J-6	C249 J-6	C250 J-6	C251 J-6	C252 J-6	C253 J-6	C254 J-6	C255 J-6	C256 J-6	C257 J-6	C258 J-6	C259 J-6	C260 J-6	C261 J-6	C262 J-6	C263 J-6	C264 J-6	C265 J-6	C266 J-6	C267 J-6	C268 J-6	C269 J-6	C270 J-6	C271 J-6	C272 J-6	C273 J-6	C274 J-6	C275 J-6	C276 J-6	C277 J-6	C278 J-6	C279 J-6	C280 J-6	C281 J-6	C282 J-6	C283 J-6	C284 J-6	C285 J-6	C286 J-6	C287 J-6	C288 J-6	C289 J-6	C290 J-6	C291 J-6	C292 J-6	C293 J-6	C294 J-6	C295 J-6	C296 J-6	C297 J-6	C298 J-6	C299 J-6	C300 J-6	C301 J-6	C302 J-6	C303 J-6	C304 J-6	C305 J-6	C306 J-6	C307 J-6	C308 J-6	C309 J-6	C310 J-6	C311 J-6	C312 J-6
	C133 A-10	C134 A-12	C135 A-11	C136 A-10	C137 A-11	C138 B-11	C139 A-12	C140 C-12	C141 C-12	C142 C-11	C143 D-11	C144 D-12	C145 D-12	C146 D-12	C147 C-11	C148 D-11	C149 C-10	C150 B-11	C151 A-4	C152 C-12	C153 B-9	C154 A-10	C155 D-13	C156 D-13	C157 E-13	C158 A-11	C159 C-13	C160 C-13	C161 C-12	C162 D-13	C163 D-12	C164 B-9	C165 B-13	C166 B-9	C167 I-12	C168 I-11	C169 I-11	C170 J-7	C171 J-7	C172 J-7	C173 J-6	C174 J-6	C175 J-6	C176 J-6	C177 J-6	C178 J-6	C179 J-6	C180 J-6	C181 J-6	C182 J-6	C183 J-6	C184 J-6	C185 J-6	C186 J-6	C187 J-6	C188 J-6	C189 J-6	C190 J-6	C191 J-6	C192 J-6	C193 J-6	C194 J-6	C195 J-6	C196 J-6	C197 J-6	C198 J-6	C199 J-6	C200 J-6	C201 J-6	C202 J-6	C203 J-6	C204 J-6	C205 J-6	C206 J-6	C207 J-6	C208 J-6	C209 J-6	C210 J-6	C211 J-6	C212 J-6	C213 J-6	C214 J-6	C215 J-6	C216 J-6	C217 J-6	C218 J-6	C219 J-6	C220 J-6	C221 J-6	C222 J-6	C223 J-6	C224 J-6	C225 J-6	C226 J-6	C227 J-6	C228 J-6	C229 J-6	C230 J-6	C231 J-6	C232 J-6	C233 J-6	C234 J-6	C235 J-6	C236 J-6	C237 J-6	C238 J-6	C239 J-6	C240 J-6	C241 J-6	C242 J-6	C243 J-6	C244 J-6	C245 J-6	C246 J-6	C247 J-6	C248 J-6	C249 J-6	C250 J-6	C251 J-6	C252 J-6	C253 J-6	C254 J-6	C255 J-6	C256 J-6	C257 J-6	C258 J-6	C259 J-6	C260 J-6	C261 J-6	C262 J-6	C263 J-6	C264 J-6	C265 J-6	C266 J-6	C267 J-6	C268 J-6	C269 J-6	C270 J-6	C271 J-6	C272 J-6	C273 J-6	C274 J-6	C275 J-6	C276 J-6	C277 J-6	C278 J-6	C279 J-6	C280 J-6	C281 J-6	C282 J-6	C283 J-6	C284 J-6	C285 J-6	C286 J-6	C287 J-6	C288 J-6	C289 J-6	C290 J-6	C291 J-6	C292 J-6	C293 J-6	C294 J-6	C295 J-6	C296 J-6	C297 J-6	C298 J-6	C299 J-6	C300 J-6	C301 J-6	C302 J-6	C303 J-6	C304 J-6	C305 J-6	C306 J-6	C307 J-6	C308 J-6	C309 J-6	C310 J-6	C311 J-6	C312 J-6
	C133 A-10	C134 A-12	C135 A-11	C136 A-10	C137 A-11	C138 B-11	C139 A-12	C140 C-12	C141 C-12	C142 C-11	C143 D-11	C144 D-12	C145 D-12	C146 D-12	C147 C-11	C148 D-11	C149 C-10	C150 B-11	C151 A-4	C152 C-12	C153 B-																																																																																																																																																															


C

[R.G.B OUT]




[REMOTE CONTROL,
HEAD AMP]


[INDICATOR,
CUSTOMER CONTROL]



[INDICATOR]




[AUDIO
OUTPUT]



3. CHASSIS

■: TA,BV3x8

7-685-646-71



No.	Part No.	Description	Remark	No.	Part No.	Description	Remark
101	*A-1340-817-A	D1 BOARD, COMPLETE		104	*A-1-536-817-31	TERMINAL BOARD ASSY, ANTENNA	
102	*A-1-237-280-11	RESISTOR ASSY, HIGH-VOLTAGE		105	*A-1-1345-618-A	D BOARD, SUB, COMPLETE	
103	*A-1-439-332-42	TRANSFORMER ASSY, FLBACK					

KV27XS-C/TC/D/XSTA

444

F

NOTE:

ELECTRICAL PARTS LIST

* Items marked " * " are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.

* All variable and adjustable resistors have characteristic curve B, unless otherwise noted.

CAPACITORS

* MF : μ F, PF : μ F

RESISTORS

* All resistors are in ohms
* F : nonflammable

COILS

* MMH : mH, UH : μ H

Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark
*A-1245-313-A F BOARD, SUB COMPLETE							

CAPACITOR				DIODE			
C601	*A-1-108-745-62	MYLAR 0.22MF	20% 300V	D601	*A-8-719-503-06	DIODE 53MB60Z	
C602	*A-1-108-745-62	MYLAR 0.22MF	20% 300V	D602	8-719-100-65	DIODE RD12E-82	
C603	*A-1-162-578-51	CERAMIC 0.0047MF	20% 400V	D603	8-719-815-55	DIODE 1S1555	
C604	*A-1-162-578-51	CERAMIC 0.0047MF	20% 400V	D604	8-759-157-40	IC UPC574J	
C605	*A-1-162-578-51	CERAMIC 0.0047MF	20% 400V	D605	8-719-901-93	DIODE V19E	
C606	*A-1-162-578-51	CERAMIC 0.0047MF	20% 400V	D606	8-719-815-55	DIODE 1S1555	
C607	*A-1-161-964-61	CERAMIC 0.0047MF	250V	D607	8-719-815-55	DIODE 1S1555	
C608	*A-1-161-964-61	CERAMIC 0.0047MF	250V	D608	8-719-815-55	DIODE 1S1555	
C609	*A-1-161-964-61	CERAMIC 0.0047MF	250V	D609	8-719-305-15	DIODE GH3F	
C610	1-125-318-00	ELECT(BLOCK) 220MF	20% 400V	D651	8-719-928-08	DIODE ERD28-08	
C611	1-110-175-81	MYLAR 0.1MF	10% 100V	D652	8-719-901-93	DIODE V19E	
C612	1-130-022-00	FILM 0.0022MF	5% 50V	D653	8-719-901-93	DIODE V19E	
C613	1-123-356-00	ELECT 10MF	20% 16V	D654	8-719-901-93	DIODE V19E	
C614	1-123-356-00	ELECT 10MF	20% 25V	D654A	8-719-924-06	DIODE ERC24-06S	
C615	1-102-106-00	CERAMIC 100PF	10% 50V	D655	8-719-901-93	DIODE V19E	
C616	1-123-369-00	ELECT 4.7MF	20% 25V	D655A	8-719-924-06	DIODE ERC24-06S	
C617	1-110-186-81	MYLAR 0.0047MF	10% 400V	D656	8-719-901-93	DIODE V19E	
C618	1-102-030-00	CERAMIC 330PF	10% 500V	D657	8-719-901-93	DIODE V19E	
C619	1-110-182-81	MYLAR 0.022MF	10% 250V	D658	8-719-102-74	DIODE RD6.2E-N2	
C620	1-123-332-00	ELECT 47MF	20% 16V	D659	8-719-102-78	DIODE RD6.8E-N2	
C621	1-136-065-00	FILM 0.0027MF	3% 2KV	D660	8-719-815-55	DIODE 1S1555	
C622	1-123-385-00	ELECT 22MF	20% 100V	D661	8-719-815-55	DIODE 1S1555	
C623	1-161-973-00	CERAMIC 220PF	10% 400V	D663	8-719-102-74	DIODE RD6.2E-N2	
C624	1-161-973-00	CERAMIC 220PF	10% 400V	D664	8-719-100-65	DIODE RD12E-82	
C625	1-123-379-00	ELECT 0.47MF	20% 50V	CONNECTOR			
C626	1-123-381-00	ELECT 2.2MF	20% 50V	F1	*1-506-349-21	3P PLUG (L)	
C627	1-123-380-00	ELECT 1MF	20% 50V	F2	*1-508-765-00	3P PLUG (M)	
C628	1-108-618-91	MYLAR 0.0022MF	10% 100V	F3	*1-508-786-00	2P PLUG (M)	
C632	1-102-002-00	CERAMIC 680PF	10% 500V	F4	*1-508-765-00	3P PLUG (M)	
C633	*A-1-108-745-62	MYLAR 0.22MF	20% 300V	F6	*1-560-123-00	PLUG, CONNECTOR (2.5MM) 3P	
C634	1-110-175-81	MYLAR 0.1MF	10% 100V	F7	*1-564-883-11	PLUG, CONNECTOR 6P	
C651	1-102-155-00	CERAMIC 330PF	20% 2KV	FUSE			
C652	1-124-347-00	ELECT 100MF	20% 160V	F601	*A-1-532-350-11	FUSE, TIME-LAG 4A/250V	
C653	1-123-364-00	ELECT 1000MF	20% 50V		1-533-149-00	HOLDER, FUSE; F601	
C654	1-123-606-00	ELECT 1000MF	20% 25V	IC			
C655	1-123-334-00	ELECT 220MF	20% 25V	IC601	8-759-100-75	IC UPC1394C	
C656	1-102-038-00	CERAMIC 0.001MF	500V	IC602	*A-8-719-800-82	DIODE TLP58K	
C656A	1-102-038-00	CERAMIC 0.001MF	500V	IC651	8-759-145-58	IC UPC4558C	
C658	1-123-332-00	ELECT 47MF	20% 16V	COIL			
C659	1-102-112-00	CERAMIC 330PF	10% 50V	L601	1-407-365-00	COIL, CHOKE	
C660	1-123-356-00	ELECT 10MF	20% 50V	L651	1-425-613-00	COIL, AIR-CORE, QF TYPE	
C661	1-123-333-00	ELECT 100MF	20% 16V	L652	1-459-442-00	COIL (WITH CORE)	
C662	1-110-190-81	MYLAR 0.01MF	10% 400V	TRANSISTOR			
C663	1-123-380-00	ELECT 1MF	20% 50V	Q601	8-729-195-82	TRANSISTOR 2SC2958	
C664	1-123-380-00	ELECT 1MF	20% 50V	Q602	8-729-301-00	TRANSISTOR 2S01497-02	
C666	1-123-307-00	ELECT 100MF	20% 6.3V		4-365-216-00	SPACER, MICA;Q602	
C667	1-102-121-00	CERAMIC 0.0022MF	10% 50V		*A-368-683-01	SPRING;Q602	
C668	1-110-190-81	MYLAR 0.01MF	10% 400V	Q603	8-729-178-54	TRANSISTOR 2SC2785	


EXPLODED VIEWS

NOTE:

- Items with no part number and no description are not stocked because they are seldom required for routine service.
- The construction parts of an assembled part are indicated with a collation number in the remark column.

- Items marked " * " are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.


1. CABINET



No.	Part No.	Description	Remark	No.	Part No.	Description	Remark
1	4-381-502-01	BUTTON, POWER (FOR GRAY)		10	*4-342-118-00	LID, SHIELD CASE, R	
2	4-381-502-11	BUTTON, POWER (FOR BLACK)		11	*4-373-212-03	LABEL, CONTROL	
3	*4-381-501-01	HOLDER, POWER SW		12	*4-381-520-01	PANEL, CONTROL	
4	Δ1-554-762-41	SWITCH, PUSH (AC POWER)(1 KEY)		13	4-373-213-01	BUTTON, MULTI	
5	*4-373-216-01	CAP. INSULATING, POWER SWITCH		14	*1-619-358-11	H1 BOARD	
6	1-503-642-11	SPEAKER		15	4-361-938-00	PUSH BUTTON (A)	
7	4-373-234-01	CLIP		16	*1-619-359-11	H2 BOARD	
8	*4-342-117-00	CASE, SHIELD (MAIN), R		17	4-373-229-01	COVER, REAR	
9	*4-333-624-00	FILM (N), SPECIAL		18	*4-381-527-01	LABEL, COMBINATION	
	*1-611-717-11	N BOARD		19	4-329-127-00	CLAMP, CORD	

2. CRT

▲: TA, BV4x12



No.	Part No.	Description	Remark	No.	Part No.	Description	Remark
51	X-4381-511-1	CABINET ASSY (FOR GRAY)	52-59	66	*1-618-883-11	J1 BOARD	
52	X-4381-511-2	CABINET ASSY (FOR BLACK)	52-59	67	3-703-003-00	SPACER, DY	
53	X-4381-510-1	LID ASSY (FOR GRAY)		68	Δ8-736-653-05	CRT (A64JK360X)	
54	X-4381-510-2	LID ASSY (FOR BLACK)		69	1-452-146-21	MAGNET, BMC	
55	X-4381-509-1	DOOR ASSY (FOR GRAY)		70	Δ1-451-255-31	DEFLECTION YOKE (SY-164)	
56	X-4381-509-2	DOOR ASSY (FOR BLACK)		71	Δ1-452-391-21	NECK ASSY, CRT (NA305)	
57	4-314-871-00	CUSHION		72	*A-1330-712-A	C BOARD, COMPLETE	
58	3-703-035-11	SHAFT, LID		73	Δ1-426-278-11	COIL, DEMAGNETIZATION	
59	4-381-503-01	PLATE, K.H. (FOR GRAY)		74	4-303-774-XX	SPRING	
60	4-381-503-11	PLATE, K.H. (FOR BLACK)		75	4-374-494-01	SCREW, SPECIAL	
61	4-381-511-01	PLATE (C), ORNAMENTAL (FOR GRAY)		76	*4-371-629-01	STOPPER, WIRE	
62	4-381-511-11	PLATE (C), ORNAMENTAL (FOR BLACK)		77	Δ1-228-544-11	RESISTOR ASSY, HIGH-VOLTAGE	
63	4-381-512-01	PLATE (D), ORNAMENTAL (FOR GRAY)		78	*A-1296-108-A	A BOARD, SUB, COMPLETE	
64	4-381-512-11	PLATE (D), ORNAMENTAL (FOR BLACK)		79	Δ1-463-577-11	TUNER, ET (BT-883A)	
65	4-374-115-01	EMBLEM, SONY		80	*A-1245-313-A	F BOARD, SUB, COMPLETE	
	X-4381-506-1	PLATE ASSY, IR(FOR GRAY)(KV-27XSC ONLY)		81	*4-375-709-01	COVER, FUSE	
	X-4381-506-2	PLATE ASSY, IR(FOR BLACK)(KV-27XSC ONLY)		82	Δ4-022-115-01	HOLDER, AC CORD	
	X-4381-508-1	PLATE ASSY, IR(FOR GRAY)(KV-27XSTC ONLY)		83	Δ1-551-270-11	CORD, POWER	
	X-4381-508-2	PLATE ASSY, IR(FOR BLACK)(KV-27XSTC ONLY)		84	4-308-870-00	CLIP, LEAD WIRE	
61	4-381-515-01	WINDOW, ORNAMENTAL		85	1-452-032-00	MAGNET, DISK; 10MM Ø	
62	4-381-514-01	PLATE, Z1 (FOR GRAY)		86	1-452-094-00	MAGNET, ROTATABLE DISK; 15MM Ø	
63	4-381-514-11	PLATE, Z1 (FOR BLACK)		87	X-4308-815-0	PERMALLOY ASSY, CONVERGENCE	
64	*4-373-234-01	CLIP		88	*A-1325-025-A	V BOARD, COMPLETE (KV-27XSTC ONLY)	
65	*4-373-228-01	HOLDER (C) (LEFT)					
	*4-373-227-01	HOLDER (C) (RIGHT)					

(KV27XSTA only)

79 Δ1-463-411-21 TUNER, ET UHF/VHF ET (UV411/CEI)

KV27XS-C/TC/D/XSTA
443

A

A V

Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark
<u>IC</u>				R110	1-215-746-91	METAL 2.2K 5% 1/6W		R181	1-215-740-91	METAL 1.7K 5% 1/6W		C040	1-136-177-00	FILM 1M 5% 50V	
IC101	8-759-909-08	IC TDA3541		R111	1-215-754-91	METAL 4.7K 5% 1/6W		R182	1-215-746-91	METAL 2.2K 5% 1/6W		C041	1-110-175-81	MYLAR 0.1MF 10% 100V	
IC102	8-759-909-54	IC TDA2546A		R112	1-215-734-91	METAL 680 5% 1/6W		R183	1-215-738-91	METAL 1K 5% 1/6W		C042	1-102-820-00	CERAMIC 330PF 5% 50V	
IC103	8-759-602-16	IC M54572L		R113	1-215-752-91	METAL 3.9K 5% 1/6W		R184	1-215-724-91	METAL 270 5% 1/6W		C043	1-123-308-00	ELECT 220MF 20% 6.3V	
IC151	8-759-007-54	IC TDA4940		R114	1-215-722-91	METAL 220 5% 1/6W		R185	1-215-726-91	METAL 330 5% 1/6W		C044	1-110-175-81	MYLAR 0.1MF 10% 100V	
IC152	8-759-007-55	IC TDA4944		R115	1-215-750-91	METAL 3.3K 5% 1/6W		R188	1-215-766-91	METAL 15K 5% 1/6W		C045	1-102-116-00	CERAMIC 680PF 10% 50V	
<u>COIL</u>				R116	1-215-730-91	METAL 470 5% 1/6W		R191	1-215-732-91	METAL 560 5% 1/6W		C046	1-123-356-00	ELECT 10MF 20% 16V	
L101	1-404-476-00	COIL, IF		R117	1-215-710-91	METAL 68 5% 1/6W		R192	1-215-732-91	METAL 560 5% 1/6W		C049	1-101-361-00	CERAMIC 150PF 10% 50V	
L102	1-404-476-00	COIL, IF		R118	1-215-724-91	METAL 270 5% 1/6W		R193	1-215-714-91	METAL 100 5% 1/6W		C050	1-101-361-00	CERAMIC 150PF 10% 50V	
L103	1-408-432-31	MICRO INDUCTOR 1.5UH		R119	1-215-730-91	METAL 470 5% 1/6W		<u>VARIABLE RESISTOR</u>				<u>TRIMMER</u>			
L104	1-408-406-00	MICRO INDUCTOR 5.6UH		R120	1-215-778-91	METAL 47K 5% 1/6W		RV101	1-228-727-00	RES, ADJ, CERAMIC CARBON 47K		CT001	1-141-181-11	CAP, TRIMMER	
L105	1-404-477-00	COIL, IF		R122	1-215-762-91	METAL 10K 5% 1/6W		RV151	1-228-726-00	RES, ADJ, CERAMIC CARBON 33K		<u>DIODE</u>			
L106	1-404-493-00	COIL		R125	1-215-736-91	METAL 820 5% 1/6W		<u>TUNER</u>				D001	8-719-911-19	DIODE 1SS119	
L107	1-404-493-00	COIL		R126	1-215-736-91	METAL 820 5% 1/6W		TU101A	1-463-577-11	TUNER, ET (BT-883A)		D002	8-719-100-35	DIODE RD5.6E-B2	
L109	1-408-409-00	MICRO INDUCTOR 10UH		R127	1-215-736-91	METAL 820 5% 1/6W		*****				D003	8-719-100-68	DIODE RD13E-B2	
L110	1-408-406-00	MICRO INDUCTOR 5.6UH		R129	1-215-810-91	METAL 1M 5% 1/6W		*A-1325-025-A V BOARD, COMPLETE (KV-27XSTC OM.Y)				D004	8-719-101-41	DIODE RD3.9E-L2	
L111	1-404-493-00	COIL		R131	1-215-778-91	METAL 47K 5% 1/6W		*****				D005	8-719-109-88	DIODE RD5.6ES-B1	
L113	1-408-226-00	MICRO INDUCTOR 82UH		R132	1-215-762-91	METAL 10K 5% 1/6W		*4-371-102-01	CASE (MAIN), SHIELD, A1		D006	8-719-911-19	DIODE 1SS119		
L114	1-407-489-00	MICRO INDUCTOR 560UH		R133	1-215-776-91	METAL 39K 5% 1/6W		*4-371-103-01	CASE (UPPER LID), SHIELD, A1		D007	8-719-911-19	DIODE 1SS119		
L116	1-408-406-00	MICRO INDUCTOR 5.6UH		R134	1-215-782-91	METAL 68K 5% 1/6W		*4-371-104-01	CASE (BOTTOM LID), SHIELD, A1		D008	8-719-911-19	DIODE 1SS119		
L117	1-408-428-00	MICRO INDUCTOR 390UH		R135	1-215-776-91	METAL 39K 5% 1/6W		<u>CAPACITOR</u>				D011	8-719-911-19	DIODE 1SS119	
L170	1-408-247-00	MICRO INDUCTOR 33MMH		R136	1-215-770-91	METAL 22K 5% 1/6W		C001	1-123-307-00	ELECT 100MF 20% 10V		D012	8-719-911-19	DIODE 1SS119	
L171	1-408-408-00	MICRO INDUCTOR 8.2UH		R137	1-215-770-91	METAL 22K 5% 1/6W		C002	1-123-332-00	ELECT 47MF 20% 16V		<u>IC</u>			
<u>TRANSISTOR</u>				R140	1-215-738-91	METAL 1K 5% 1/6W		C003	1-123-309-00	ELECT 330MF 20% 6.3V		IC001	8-759-918-54	IC SAA5230	
Q101	8-729-178-54	TRANSISTOR 2SC2785		R141	1-215-766-91	METAL 15K 5% 1/6W		C004	1-123-332-00	ELECT 47MF 20% 16V		IC002	8-759-918-56	IC SAA5240A	
Q102	8-729-105-47	TRANSISTOR 2SC2026-L		R142	1-215-786-91	METAL 100K 5% 1/6W		C005	1-123-308-00	ELECT 220MF 20% 6.3V		*1-526-722-00 SOCKET, IC 40P; IC002			
Q103	8-729-117-54	TRANSISTOR 2SA1175		R143	1-215-786-91	METAL 100K 5% 1/6W		C006	1-123-321-00	ELECT 220MF 20% 16V		IC003	8-759-206-27	IC TC5564PL-15	
Q104	8-729-900-36	TRANSISTOR DTC124ES		R144	1-215-752-91	METAL 3.9K 5% 1/6W		C007	1-110-175-81	MYLAR 0.1MF 10% 100V		IC004	8-759-108-76	IC CX526-050	
Q105	8-729-117-54	TRANSISTOR 2SA1175		R145	1-215-752-91	METAL 3.9K 5% 1/6W		C008	1-102-951-00	CERAMIC 15PF 5% 50V		<u>COIL</u>			
Q151	8-729-178-54	TRANSISTOR 2SC2785		R146	1-215-754-91	METAL 4.7K 5% 1/6W		C009	1-102-074-00	CERAMIC 0.001MF 10% 50V		L001	1-408-411-00	MICRO INDUCTOR 15UH	
Q152	8-729-178-54	TRANSISTOR 2SC2785		R151	1-215-736-91	METAL 820 5% 1/6W		C010	1-102-824-00	CERAMIC 470PF 5% 50V		<u>TRANSISTOR</u>			
Q153	8-729-178-54	TRANSISTOR 2SC2785		R152	1-215-776-91	METAL 39K 5% 1/6W		C011	1-110-182-81	MYLAR 0.022MF 10% 250V		Q001	8-729-109-53	TRANSISTOR 2SD795A	
Q154	8-729-900-89	TRANSISTOR DTC144ES		R153	1-215-728-91	METAL 390 5% 1/6W		C012	1-102-980-00	CERAMIC 270PF 5% 50V		Q002	8-729-178-54	TRANSISTOR 2SC2785	
Q155	8-729-178-54	TRANSISTOR 2SC2785		R154	1-215-714-91	METAL 100 5% 1/6W		C013	1-102-973-00	CERAMIC 100PF 5% 50V		Q003	8-729-177-43	TRANSISTOR 2SD774	
Q156	8-729-178-54	TRANSISTOR 2SC2785		R155	1-215-770-91	METAL 22K 5% 1/6W		C014	1-102-851-00	CERAMIC 15PF 5% 50V		Q004	8-729-117-54	TRANSISTOR 2SA1175	
Q157	8-729-900-89	TRANSISTOR DTC144ES		R156	1-215-784-91	METAL 82K 5% 1/6W		C015	1-102-883-00	CERAMIC 27PF 5% 50V		Q005	8-729-900-89	TRANSISTOR DTC144ES	
Q158	8-729-900-89	TRANSISTOR DTC144ES		R157	1-215-754-91	METAL 4.7K 5% 1/6W		C016	1-110-190-81	MYLAR 0.01MF 10% 400V		Q006	8-729-117-54	TRANSISTOR 2SA1175	
Q172	8-729-117-54	TRANSISTOR 2SA1175		R158	1-215-754-91	METAL 4.7K 5% 1/6W		C017	1-110-171-81	MYLAR 0.047MF 10% 100V		Q007	8-729-178-54	TRANSISTOR 2SC2785	
Q173	8-729-178-54	TRANSISTOR 2SC2785		R159	1-215-754-91	METAL 4.7K 5% 1/6W		C018	1-102-953-00	CERAMIC 18PF 5% 50V		Q008	8-729-178-54	TRANSISTOR 2SC2785	
Q174	8-729-178-54	TRANSISTOR 2SC2785		R160	1-215-754-91	METAL 4.7K 5% 1/6W		C019	1-110-171-81	MYLAR 0.047MF 10% 100V		Q009	8-729-900-89	TRANSISTOR DTC144ES	
Q175	8-729-178-54	TRANSISTOR 2SC2785		R161	1-215-738-91	METAL 1K 5% 1/6W		C020	1-102-978-00	CERAMIC 220PF 5% 50V		Q010	8-729-117-54	TRANSISTOR 2SA1175	
<u>RESISTOR</u>				R162	1-215-738-91	METAL 1K 5% 1/6W		C021	1-110-173-81	MYLAR 0.068MF 10% 100V		Q011	8-729-117-54	TRANSISTOR 2SA1175	
R101	1-215-738-91	METAL 1K 5% 1/6W		R166	1-215-750-91	METAL 3.3K 5% 1/6W		C022	1-102-963-00	CERAMIC 33PF 5% 50V		Q012	8-729-117-54	TRANSISTOR 2SA1175	
R102	1-215-738-91	METAL 1K 5% 1/6W		R167	1-215-774-91	METAL 33K 5% 1/6W		C023	1-102-963-00	CERAMIC 33PF 5% 50V					
R105	1-215-760-91	METAL 8.2K 5% 1/6W		R168	1-215-770-91	METAL 22K 5% 1/6W		C024	1-136-177-00	FILM 1MF 5% 50V					
R106	1-215-750-91	METAL 3.3K 5% 1/6W		R172	1-215-720-91	METAL 180 5% 1/6W		C025	1-123-298-00	ELECT 470MF 20% 6.3V					
R107	1-215-750-91	METAL 3.3K 5% 1/6W		R173	1-215-778-91	METAL 47K 5% 1/6W		C026	1-102-973-00	CERAMIC 100PF 5% 50V					
R108	1-215-798-91	METAL 330K 5% 1/6W		R174	1-215-796-91	METAL 270K 5% 1/6W									
R109	1-215-746-91	METAL 2.2K 5% 1/6W		R175	1-215-772-91	METAL 27K 5% 1/6W									
				R176	1-215-738-91	METAL 1K 5% 1/6W									
				R177	1-215-762-91	METAL 10K 5% 1/6W									
				R178	1-215-762-91	METAL 10K 5% 1/6W									
				R179	1-215-762-91	METAL 10K 5% 1/6W									
				R180	1-215-738-91	METAL 1K 5% 1/6W									

A

445

C D1

Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark
SG703	1-519-063-XX	DISCHARGING GAP		TRANSISTOR			
*****				Q1501	8-729-178-54	TRANSISTOR 2SC2785	
*A-1340-817-A D1 BOARD, COMPLETE				Q1502	8-729-178-54	TRANSISTOR 2SC2785	
*****				Q1503	8-729-374-02	TRANSISTOR 2SB740	
				Q1504	8-729-195-82	TRANSISTOR 2SC2958	
CAPACITOR				RESISTOR			
C1501	1-108-630-91	MYLAR 0.022MF	10% 100V	R1501	1-247-805-00	CARBON 82 5% 1/6W	
C1503	1-106-196-00	MYLAR 0.01MF	10% 100V	R1502	1-247-145-00	CARBON 3.9K 5% 1/4W	
C1504	1-123-380-00	ELECT 1MF	20% 50V	R1503	1-249-415-11	CARBON 680 5% 1/6W	
C1505	1-108-622-91	MYLAR 0.0047MF	10% 100V	R1504	1-249-432-11	CARBON 18K 5% 1/6W	
C1506	1-123-382-00	ELECT 3.3MF	20% 50V	R1505	1-249-423-11	CARBON 3.3K 5% 1/6W	
C1507	1-123-357-00	ELECT 22MF	20% 50V	R1506	1-249-432-11	CARBON 18K 5% 1/6W	
C1508	1-123-379-00	ELECT 0.47MF	20% 50V	R1508	1-249-432-11	CARBON 18K 5% 1/6W	
C1509	1-123-360-00	ELECT 100MF	20% 50V	R1509	1-247-702-11	CARBON 150 5% 1/4W	
C1510	1-123-381-00	ELECT 2.2MF	20% 50V	R1510	1-249-417-11	CARBON 1K 5% 1/6W	
C1511	1-123-380-00	ELECT 1MF	20% 50V	R1511	1-246-533-00	CARBON 330K 5% 1/4W	
C1512	1-106-196-00	MYLAR 0.01MF	10% 100V	R1512	1-247-891-00	CARBON 330K 5% 1/6W	
C1513	1-123-332-00	ELECT 47MF	20% 16V	R1513	1-247-829-00	CARBON 820 5% 1/6W	
C1514	1-123-330-00	ELECT 22MF	20% 16V	R1514	1-247-815-00	CARBON 220 5% 1/6W	
C1515	1-123-330-00	ELECT 22MF	20% 16V	R1515	1-246-535-00	CARBON 390K 5% 1/4W	
C1516	1-123-360-00	ELECT 100MF	20% 50V	R1516	1-249-429-11	CARBON 10K 5% 1/6W	
C1517	1-123-382-00	ELECT 3.3MF	20% 50V	R1517	1-247-721-11	CARBON 4.7K 5% 1/4W	
C1518	1-106-192-00	MYLAR 0.0068MF	10% 100V	R1518	1-249-465-11	CARBON 47K 5% 1/4W	
C1519	1-106-208-00	MYLAR 0.033MF	10% 100V	R1519	1-249-419-11	CARBON 1.5K 5% 1/6W	
C1520	1-123-333-00	ELECT 100MF	20% 16V	R1520	1-247-839-00	CARBON 2.2K 5% 1/6W	
C1521	1-108-637-00	MYLAR 0.082MF	10% 100V	R1521	1-249-435-11	CARBON 33K 5% 1/6W	
C1522	1-108-630-91	MYLAR 0.022MF	10% 100V	R1522	1-249-435-11	CARBON 33K 5% 1/6W	
C1523	1-123-356-00	ELECT 10MF	20% 16V	R1523	1-247-853-00	CARBON 8.2K 5% 1/6W	
C1524	1-108-622-91	MYLAR 0.0047MF	10% 100V	R1524	1-247-811-00	CARBON 150 5% 1/6W	
C1525	1-129-701-00	FILM 0.01MF	5% 100V	R1525	1-249-429-11	CARBON 10K 5% 1/6W	
C1526	1-102-125-00	CERAMIC 0.0047MF	10% 50V	R1526	1-247-725-11	CARBON 10K 5% 1/4W	
C1527	1-136-165-00	FILM 0.1MF	5% 50V	R1527	1-247-787-00	CARBON 15 5% 1/6W	
CONNECTOR				R1528	1-249-414-11	CARBON 560 5% 1/6W	
CNJ1	*1-562-370-21	CONNECTOR, BOARD TO BOARD 18P		R1529	1-249-434-11	CARBON 27K 5% 1/6W	
DIODE				R1530	1-216-451-11	METAL OXIDE 120 5% 2W	F
D1501	8-719-911-19	DIODE 1SS119		R1531	1-215-865-11	METAL OXIDE 220 5% 1W	F
D1502	8-719-911-19	DIODE 1SS119		R1532	1-247-809-00	CARBON 120 5% 1/6W	
IC				R1533	1-247-242-00	CARBON 1.2K 5% 1/2W	
IC1501	8-759-905-39	IC TDA1082		R1534	1-247-803-00	CARBON 68 5% 1/6W	
COIL				R1535	1-216-423-11	METAL OXIDE 27 5% 1W	F
L1501	1-408-245-00	MICRO INDUCTOR 22MMH		R1536	1-247-869-00	CARBON 3K 5% 1/6W	
L1502	1-407-509-00	MICRO INDUCTOR 27MMH		VARIABLE RESISTOR			
L1503	1-408-242-00	MICRO INDUCTOR 10MMH		RV1501	1-230-625-11	RES, ADJ, CARBON 330	
L1504	1-408-247-00	MICRO INDUCTOR 33MMH		RV1502	1-230-634-51	RES, ADJ, CARBON 100K	
				RV1503	1-230-634-51	RES, ADJ, CARBON 100K	
				RV1504	1-226-771-00	RES, ADJ, METAL GLAZE 1K	
				RV1505	1-230-628-11	RES, ADJ, CARBON 2.2K	
				RV1506	1-230-634-51	RES, ADJ, CARBON 100K	
				RV1507	1-230-630-11	RES, ADJ, CARBON 10K	
				RV1508	1-230-627-11	RES, ADJ, CARBON 1K	
				RV1509	1-230-271-00	RES, ADJ, CARBON 4.7K	

D1 D

Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark
RV1510	1-230-630-11	RES, ADJ, CARBON 10K		C219	1-123-330-00	ELECT 10MF	20% 16V
RV1511	1-230-625-11	RES, ADJ, CARBON 330		C220	1-106-212-00	MYLAR 0.047MF	10% 100V
THERMISTOR				C221	1-108-614-91	MYLAR 0.001MF	10% 100V
TH1501	1-806-110-00	THERMISTOR		C222	1-123-322-00	ELECT 330MF	20% 16V
TH1502	1-800-625-00	THERMISTOR		C223	1-123-380-00	ELECT 1MF	20% 50V
*****				C224	1-123-380-00	ELECT 1MF	20% 50V
A-1345-618-A D BOARD, SUB COMPLETE				C225	1-123-322-00	MYLAR 330MF	20% 16V
*****				C226	1-123-330-00	ELECT 22MF	20% 16V
4-303-483-00 HEAD, WASHER, TAPPING SCREW				C227	1-123-330-00	ELECT 22MF	20% 16V
CAPACITOR				C228	1-102-945-00	CERAMIC 8PF	1PF 50V
C001	1-123-307-00	ELECT 100MF	20% 10V	C229	1-102-108-00	CERAMIC 150PF	10% 50V
C002	1-123-381-00	ELECT 2.2MF	20% 50V	C230	1-106-208-00	MYLAR 0.033MF	10% 100V
C003	1-102-973-00	CERAMIC 100PF	5% 50V	C231	1-123-333-00	ELECT 100MF	20% 16V
C004	1-108-603-00	MYLAR 0.1MF	5% 50V	C232	1-123-330-00	ELECT 22MF	20% 16V
C005	1-123-356-00	ELECT 10MF	20% 50V	C233	1-102-114-00	CERAMIC 470PF	10% 50V
C006	1-102-959-00	CERAMIC 22PF	5% 50V	C234	1-123-379-00	ELECT 0.47MF	20% 50V
C007	1-102-963-00	CERAMIC 33PF	5% 50V	C235	1-123-330-00	ELECT 22MF	20% 16V
C008	1-123-356-00	ELECT 10MF	20% 50V	C236	1-102-114-00	CERAMIC 470PF	10% 50V
C009	1-102-114-00	CERAMIC 470PF	10% 50V	C237	1-123-379-00	ELECT 0.47MF	20% 50V
C010	1-123-369-00	ELECT 4.7MF	20% 25V	C238	1-108-603-00	MYLAR 0.1MF	5% 50V
C011	1-124-253-00	ELECT 0.47MF	20% 50V	C239	1-108-603-00	MYLAR 0.1MF	5% 50V
C012	1-101-004-00	CERAMIC 0.01MF	50V	C240	1-108-603-00	ELECT 0.1MF	5% 50V
C015	1-123-381-00	ELECT 2.2MF	20% 50V	C241	1-124-472-11	ELECT 470MF	20% 10V
C016	1-101-810-00	CERAMIC 100PF	5% 500V	C243	1-123-332-00	ELECT 47MF	20% 16V
C017	1-123-306-00	ELECT 47MF	20% 10V	C244	1-102-114-00	CERAMIC 470PF	10% 50V
C017A	1-123-307-00	ELECT 100MF	20% 10V	C245	1-102-114-00	CERAMIC 470PF	10% 50V
C018	1-106-220-00	MYLAR 0.1MF	10% 100V	C272	1-108-603-00	MYLAR 0.1MF	5% 50V
C019	1-123-306-00	ELECT 47MF	20% 10V	C273	1-123-359-00	ELECT 47MF	20% 50V
C020	1-102-112-00	CERAMIC 330PF	10% 50V	C274	1-123-364-00	ELECT 1000MF	20% 50V
C022	1-161-377-00	CERAMIC 0.0047MF	20% 50V	C276	1-123-359-00	ELECT 47MF	20% 50V
C026	1-102-074-00	CERAMIC 0.001MF	10% 50V	C277	1-108-603-00	MYLAR 0.1MF	5% 50V
C027	1-123-307-00	ELECT 100MF	20% 10V	C278	1-123-349-00	ELECT 1000MF	20% 35V
C201	1-102-114-00	CERAMIC 470PF	10% 50V	C279	1-123-343-00	ELECT 33MF	20% 25V
C202	1-102-074-00	CERAMIC 0.001MF	10% 50V	C280	1-123-349-00	ELECT 1000MF	20% 35V
C203	1-123-380-00	ELECT 1MF	20% 50V	C281	1-123-360-00	ELECT 100MF	20% 50V
C204	1-102-114-00	CERAMIC 470PF	10% 50V	C282	1-101-005-00	CERAMIC 0.022MF	50V
C205	1-123-356-00	ELECT 10MF	20% 16V	C283	1-101-005-00	CERAMIC 0.022MF	50V
C206	1-102-074-00	CERAMIC 0.001MF	10% 50V	C284	1-102-106-00	CERAMIC 100PF	10% 50V
C207	1-123-369-00	ELECT 1MF	20% 50V	C285	1-102-106-00	CERAMIC 100PF	10% 50V
C208	1-123-332-00	ELECT 47MF	20% 16V	C288	1-108-630-91	MYLAR 0.022MF	10% 100V
C209	1-106-212-00	MYLAR 0.047MF	10% 100V	C289	1-108-630-91	MYLAR 0.022MF	10% 100V
C210	1-108-614-91	MYLAR 0.001MF	10% 100V	C290	1-123-343-00	ELECT 33MF	20% 25V
C211	1-123-380-00	ELECT 1MF	20% 50V	C291	1-123-343-00	ELECT 33MF	20% 25V
C212	1-123-369-00	ELECT 4.7MF	20% 50V	C301	1-102-944-00	CERAMIC 7PF	1PF 50V
C213	1-123-356-00	ELECT 10MF	20% 16V	C302	1-102-944-00	CERAMIC 7PF	1PF 50V
C214	1-123-356-00	ELECT 10MF	20% 16V	C303	1-102-951-00	CERAMIC 15PF	5% 50V
C215	1-123-356-00	ELECT 10MF	20% 16V	C304	1-102-816-00	CERAMIC 120PF	5% 50V
C216	1-123-356-00	ELECT 10MF	20% 16V	C308	1-123-356-00	ELECT 10MF	20% 16V
C217	1-102-074-00	CERAMIC 0.001MF	10% 50V	C309	1-123-380-00	ELECT 1MF	20% 50V
C218	1-106-208-00	MYLAR 0.033MF	10% 100V	C311	1-123-323-00	ELECT 470MF	20% 16V
				C312	1-123-279-00	ELECT 2.2MF	20% 50V
				C313	1-123-356-00	ELECT 10MF	20% 25V
				C314	1-123-381-00	ELECT 2.2MF	20% 50V



Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark
RESISTOR				CRYSTAL			
R001	1-215-867-00	METAL OXIDE 470 5% 1W F		X001	1-567-162-00	OSCILLATOR, CRYSTAL	
R002	1-215-762-91	METAL 10K 5% 1/6W		X002	1-567-495-11	OSCILLATOR, CRYSTAL	
R003	1-215-778-91	METAL 47K 5% 1/6W		X003	1-567-192-11	OSCILLATOR, CERAMIC	
R004	1-247-745-11	CARBON 330 5% 1/2W		*****			
R005	1-215-736-91	METAL 820 5% 1/6W		*A-1330-712-A C BOARD, COMPLETE			
R006	1-215-754-91	METAL 4.7K 5% 1/6W		*****			
R007	1-215-726-91	METAL 330 5% 1/6W		A1-526-644-41 SOCKET, CRT			
R008	1-215-780-91	METAL 56K 5% 1/6W		CONNECTOR			
R009	1-215-738-91	METAL 1K 5% 1/6W		C1	*1-508-765-00	3P PLUG (M)	
R010	1-215-770-91	METAL 22K 5% 1/6W		C2	*1-564-879-31	PLUG, CONNECTOR 2P	
R011	1-215-738-91	METAL 1K 5% 1/6W		C3	*1-564-880-31	PLUG, CONNECTOR 3P	
R012	1-215-762-91	METAL 10K 5% 1/6W		C4	*1-564-884-31	PLUG, CONNECTOR 7P	
R013	1-215-738-91	METAL 1K 5% 1/6W		C5	*1-508-766-00	4P PLUG (M)	
R014	1-215-738-91	METAL 1K 5% 1/6W		C6	*1-508-784-00	1P PLUG	
R015	1-215-738-91	METAL 1K 5% 1/6W		CAPACITOR			
R016	1-215-132-00	METAL 150 5% 1/4W		C701	1-102-116-00	CERAMIC 680PF 10% 50V	
R017	1-215-132-00	METAL 150 5% 1/4W		C702	1-102-116-00	CERAMIC 680PF 10% 50V	
R018	1-215-132-00	METAL 150 5% 1/4W		C703	1-102-116-00	CERAMIC 680PF 10% 50V	
R019	1-215-132-00	METAL 150 5% 1/4W		C704	1-102-945-00	CERAMIC 8PF 1PF 50V	
R020	1-215-716-91	METAL 120 5% 1/6W		C705	1-102-945-00	CERAMIC 8PF 1PF 50V	
R021	1-215-716-91	METAL 120 5% 1/6W		C706	1-102-945-00	CERAMIC 8PF 1PF 50V	
R022	1-215-716-91	METAL 120 5% 1/6W		C709	1-123-356-00	ELECT 10MF 20% 16V	
R023	1-215-776-91	METAL 39K 5% 1/6W		C711	1-102-963-00	CERAMIC 33PF 5% 50V	
R024	1-215-756-91	METAL 5.6K 5% 1/6W		C712	1-102-963-00	CERAMIC 33PF 5% 50V	
R025	1-215-746-91	METAL 2.2K 5% 1/6W		C713	1-102-963-00	CERAMIC 33PF 5% 50V	
R040	1-215-714-91	METAL 100 5% 1/6W		C731	1-123-356-00	ELECT 10MF 20% 16V	
R044	1-217-376-00	FUSIBLE 1.2 5% 1/4W F		C732	1-101-006-00	CERAMIC 0.047MF 50V	
R046	1-215-726-91	METAL 330 5% 1/6W		C733	1-123-356-00	ELECT 10MF 20% 25V	
R047	1-215-762-91	METAL 10K 5% 1/6W		C735	1-123-356-00	ELECT 10MF 20% 25V	
R048	1-215-764-91	METAL 12K 5% 1/6W		C737	1-123-254-00	ELECT 10MF 250V	
R049	1-215-690-91	METAL 10 5% 1/6W		C741	1-129-714-00	FILM 0.01MF 10% 630V	
R052	1-215-738-91	METAL 1K 5% 1/6W		C742	1-102-249-00	CERAMIC 680PF 20% 2KV	
R065	1-215-738-91	METAL 1K 5% 1/6W		C751	1-101-361-00	CERAMIC 150PF 5% 50V	
VARIABLE RESISTOR				C752	1-108-617-91	MYLAR 0.0018MF 10% 100V	
RV001	1-230-631-11	RES, ADJ, CARBON 22K		C753	1-106-196-00	MYLAR 0.01MF 10% 100V	
RV002	1-224-247-XX	RES, ADJ, METAL GLAZE 100		C754	1-102-98C-00	CERAMIC 270PF 5% 50V	
CONNECTOR				C757	1-106-22C-00	MYLAR 0.1MF 10% 100V	
V1	*1-560-124-00	PLUG, CONNECTOR (2.5MM PITCH)		C759	1-123-356-00	ELECT 10MF 20% 50V	
V2	*1-560-124-00	PLUG, CONNECTOR (2.5MM PITCH)		C760	1-123-38C-00	ELECT 33MF 20% 50V	
V4	*1-560-124-00	PLUG, CONNECTOR (2.5MM PITCH)		C761	1-101-006-00	CERAMIC 0.047MF 50V	
V5	*1-560-124-00	PLUG, CONNECTOR (2.5MM PITCH)		C762	1-106-196-00	MYLAR 0.01MF 10% 100V	
V6	*1-508-784-00	1P PLUG		DIODE			
V9	*1-560-126-00	PLUG, CONNECTOR (2.5MM PITCH)		D701	8-719-911-19	DIODE 1SS119	
V10	*1-508-784-00	1P PLUG		D702	8-719-911-19	DIODE 1SS119	
V11	*1-560-124-00	PLUG, CONNECTOR (2.5MM) 4P		D703	8-719-911-19	DIODE 1SS119	
V12	*1-560-123-00	PLUG, CONNECTOR (2.5MM) 3P		D704	8-719-911-19	DIODE 1SS119	
V13	*1-560-127-00	PLUG, CONNECTOR (2.5MM) 7P					

Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark
D705	8-719-911-19	DIODE 1SS119		R721	1-249-420-11	CARBON 1.8K 5% 1/6W	
D706	8-719-911-19	DIODE 1SS119		R722	1-249-419-11	CARBON 1.5K 5% 1/6W	
D707	8-719-911-19	DIODE 1SS119		R723	1-249-419-11	CARBON 1.5K 5% 1/6W	
D708	8-719-911-19	DIODE 1SS119		R724	1-249-419-11	CARBON 1.5K 5% 1/6W	
D709	8-719-911-19	DIODE 1SS119		R725	1-214-961-00	METAL 750K 1% 1/4W	
COIL				R726	1-214-956-00	METAL 470K 1% 1/4W	
L701	1-408-420-00	MICRO INDUCTOR 82UH		R727	1-214-787-00	METAL 270K 1% 1/4W	
L751	1-408-413-00	MICRO INDUCTOR 22UH		R730	1-247-815-00	CARBON 220 5% 1/6W	
TRANSISTOR				R731	1-247-851-00	CARBON 6.8K 5% 1/6W	
Q701	8-729-255-12	TRANSISTOR 2SC2551		R732	1-214-961-00	METAL 750K 1% 1/4W	
Q702	8-729-255-12	TRANSISTOR 2SC2551		R733	1-247-236-00	CARBON 680 5% 1/2W	
Q703	8-729-255-12	TRANSISTOR 2SC2551		R734	1-247-839-00	CARBON 2.2K 5% 1/6W	
Q704	8-729-326-11	TRANSISTOR 2SC2611		R735	1-247-799-00	CARBON 47 5% 1/6W	
	4-303-483-00	HEAD, WASHER, TAPPING SCREW;Q704		R736	1-249-417-11	CARBON 1K 5% 1/6W	
Q705	8-729-326-11	TRANSISTOR 2SC2611		R737	1-215-878-00	METAL OXIDE 33K 5% 1W F	
Q706	8-729-326-11	TRANSISTOR 2SC2611		R738	1-215-878-00	METAL OXIDE 33K 5% 1W F	
Q707	8-729-200-17	TRANSISTOR 2SA1091		R739	1-215-878-00	METAL OXIDE 33K 5% 1W F	
Q708	8-729-200-17	TRANSISTOR 2SA1091		R740	1-249-405-11	CARBON 100 5% 1/6W F	
Q709	8-729-200-17	TRANSISTOR 2SA1091		R741	1-207-458-00	WIREWOUND 0.39 10% 1/2W	
Q710	8-729-802-47	TRANSISTOR 2SC3504		R742	1-202-838-00	SOL ID 100K 10% 1/2W	
Q711	8-729-802-47	TRANSISTOR 2SC3504		R743	1-249-429-11	CARBON 10K 5% 1/6W	
Q712	8-729-802-47	TRANSISTOR 2SC3504		R744	1-202-844-00	SOL ID 330K 10% 1/2W	
Q713	8-729-117-54	TRANSISTOR 2SA1175		R745	1-202-842-91	SOL ID 220K 10% 1/2W	
Q714	8-729-900-36	TRANSISTOR DT124ES		R746	1-202-821-11	SOL ID 1.8K 10% 1/2W	
Q715	8-729-178-54	TRANSISTOR 2SC2785		R747	1-202-821-11	SOL ID 1.8K 10% 1/2W	
Q751	8-729-178-54	TRANSISTOR 2SC2785		R748	1-202-821-11	SOL ID 1.8K 10% 1/2W	
Q752	8-729-178-54	TRANSISTOR 2SC2785		R751	1-247-833-00	CARBON 1.2K 5% 1/6W	
Q753	8-729-103-43	TRANSISTOR 2S8734		R752	1-247-849-00	CARBON 5.6K 5% 1/6W	
Q754	8-729-177-43	TRANSISTOR 2SD0774		R753	1-249-414-11	CARBON 560 5% 1/6W	
RESISTOR				R754	1-249-434-11	CARBON 27K 5% 1/6W	
R701	1-216-485-11	METAL OXIDE 5.6K 5% 3W F		R755	1-249-405-11	CARBON 100 5% 1/6W	
R702	1-216-485-11	METAL OXIDE 5.6K 5% 3W F		R756	1-249-419-11	CARBON 1.5K 5% 1/6W	
R703	1-216-485-11	METAL OXIDE 5.6K 5% 3W F		R757	1-249-405-11	CARBON 100 5% 1/6W	
R704	1-247-710-11	CARBON 560 5% 1/4W F		R758	1-247-815-00	CARBON 220 5% 1/6W	
R705	1-247-710-11	CARBON 560 5% 1/4W F		R760	1-247-819-00	CARBON 330 5% 1/6W	
R706	1-247-710-11	CARBON 560 5% 1/4W F		R761	1-249-429-11	CARBON 10K 5% 1/6W	
R707	1-249-417-11	CARBON 1K 5% 1/6W		R762	1-247-895-00	CARBON 470K 5% 1/6W	
R708	1-249-417-11	CARBON 1K 5% 1/6W		R763	1-249-429-11	CARBON 10K 5% 1/6W	
R709	1-249-417-11	CARBON 1K 5% 1/6W		R764	1-249-455-11	CARBON 4.7 5% 1/4W F	
R710	1-214-909-00	METAL 68K 1% 1/2W		R765	1-249-455-11	CARBON 4.7 5% 1/4W F	
R711	1-214-909-00	METAL 68K 1% 1/2W		R766	1-247-833-00	CARBON 1.2K 5% 1/6W	
R712	1-214-909-00	METAL 68K 1% 1/2W		R767	1-249-420-11	CARBON 1.8K 5% 1/6W	
R713	1-247-839-00	CARBON 2.2K 5% 1/6W		R768	1-216-449-11	METAL OXIDE 56 5% 2W F	
R714	1-237-839-00	CARBON 2.2K 5% 1/6W		R769	1-217-403-00	FUSIBLE 220 5% 1/4W F	
R715	1-249-423-11	CARBON 3.3K 5% 1/6W		VARIABLE RESISTOR			
R716	1-249-429-11	CARBON 10K 5% 1/6W		RV701	1-230-105-00	RES, ADJ, CARBON 3.3K	
R717	1-249-429-11	CARBON 10K 5% 1/6W		RV702	1-230-103-00	RES, ADJ, CARBON 2.2K	
R718	1-249-429-11	CARBON 10K 5% 1/6W		RV741	1-230-641-11	RES, ADJ, METAL GLAZE 2.2M	
R719	1-249-425-11	CARBON 4.7K 5% 1/6W		SPARK GAP			
R720	1-249-420-11	CARBON 1.8K 5% 1/6W		S6701	1-519-063-XX	DISCHARGING GAP	
				S6702	1-519-063-XX	DISCHARGING GAP	



Ref.No.	Part No.	Description
L304	1-408-602-21	MICRO INDUCTOR 8.2UH
L306	1-410-260-11	MICRO INDUCTOR 33UH
L307	1-410-261-11	MICRO INDUCTOR 5.6UH
L308	1-408-415-00	MICRO INDUCTOR 33UH
L310	1-407-705-00	MICRO INDUCTOR 100UH
L311	1-408-227-00	MICRO INDUCTOR 470UH
L801	1-407-365-00	COIL, CHOKE
L802	1-459-585-11	COIL (WITH CORE) (DRUM TYPE)
L803	1-459-224-00	H.C
L804	1-421-390-00	COIL, FERRITE (PMC)
L805	1-408-239-00	MICRO INDUCTOR 4.7MH
L806	1-421-329-00	COIL, CHOKE
L808	1-407-365-00	COIL, CHOKE
L809	1-437-090-00	HOT
L810	1-407-365-00	COIL, CHOKE
L811	1-459-074-00	COIL, DUST CORE 6.8MH(HCC)
TRANSISTOR		
Q001	8-729-117-54	TRANSISTOR 2SA1175
Q003	8-729-178-54	TRANSISTOR 2SC2785
Q004	8-729-178-54	TRANSISTOR 2SC2785
Q006	8-729-178-54	TRANSISTOR 2SC2785
Q007	8-729-603-50	TRANSISTOR 2SC403SP
Q008	8-729-178-54	TRANSISTOR 2SC2785
Q009	8-729-178-54	TRANSISTOR 2SC2785
Q011	8-729-178-54	TRANSISTOR 2SC2785
Q201	8-729-178-54	TRANSISTOR 2SC2785
Q206	8-729-178-54	TRANSISTOR 2SC2785
Q207	8-729-117-54	TRANSISTOR 2SA1175
Q208	8-729-117-54	TRANSISTOR 2SA1175
Q301	8-729-178-54	TRANSISTOR 2SC2785
Q305	8-729-178-54	TRANSISTOR 2SC2785
Q309	8-729-178-54	TRANSISTOR 2SC2785
Q310	8-729-178-54	TRANSISTOR 2SC2785
Q311	8-729-178-54	TRANSISTOR 2SC2785
Q312	8-729-178-54	TRANSISTOR 2SC2785
Q313	8-729-178-54	TRANSISTOR 2SC2785
Q320	8-729-603-50	TRANSISTOR 2SC403SP
Q502	8-729-117-54	TRANSISTOR 2SA1175
Q504	8-729-117-54	TRANSISTOR 2SA1175
Q505	8-729-168-82	TRANSISTOR 2SC2688
Q506	8-729-169-02	TRANSISTOR 2SC2690A
Q507	8-729-122-02	TRANSISTOR 2SA1220A
Q508	8-729-195-82	TRANSISTOR 2SC2958
Q510	8-729-178-54	TRANSISTOR 2SC2785
Q511	8-729-178-54	TRANSISTOR 2SC2785
Q512	8-729-900-36	TRANSISTOR DTC124ES
Q514	8-729-178-54	TRANSISTOR 2SC2785
Q515	8-729-178-54	TRANSISTOR 2SC2785
Q551	8-729-177-43	TRANSISTOR 2SD174
Q552	8-729-374-02	TRANSISTOR 2SB740
Q802	8-729-300-90	TRANSISTOR 2SD1497-06
Q803	8-719-801-06	THYRISTOR 56344G

Remark	Ref.No.	Part No.	Description
			RESISTOR
	R001	1-249-417-11	CARBON 1K 5% 1/6W
	R002	1-249-417-11	CARBON 1K 5% 1/6W
	R003	1-249-417-11	CARBON 1K 5% 1/6W
	R004	1-247-815-00	CARBON 220 5% 1/6W
	R005	1-247-815-00	CARBON 220 5% 1/6W
	R006	1-247-815-00	CARBON 220 5% 1/6W
	R007	1-247-815-00	CARBON 220 5% 1/6W
	R008	1-247-815-00	CARBON 220 5% 1/6W
	R009	1-247-815-00	CARBON 220 5% 1/6W
	R010	1-247-815-00	CARBON 220 5% 1/6W
	R011	1-247-815-00	CARBON 220 5% 1/6W
	R012	1-247-799-00	CARBON 47 5% 1/6W
	R013	1-247-815-00	CARBON 220 5% 1/6W
	R014	1-249-425-11	CARBON 4.7K 5% 1/6W
	R015	1-249-425-11	CARBON 4.7K 5% 1/6W
	R016	1-247-721-11	CARBON 4.7K 5% 1/4W
	R017	1-247-713-11	CARBON 1K 5% 1/4W
	R018	1-249-417-11	CARBON 1K 5% 1/6W
	R020	1-249-437-11	CARBON 47K 5% 1/6W
	R021	1-247-859-00	CARBON 15K 5% 1/6W
	R022	1-247-859-00	CARBON 15K 5% 1/6W
	R023	1-249-405-11	CARBON 100 5% 1/6W
	R024	1-249-417-11	CARBON 1K 5% 1/6W
	R025	1-249-433-11	CARBON 22K 5% 1/6W
	R026	1-247-859-00	CARBON 15K 5% 1/6W
	R027	1-247-708-11	CARBON 470 5% 1/4W
	R028	1-247-163-00	CARBON 22K 5% 1/4W
	R029	1-249-433-11	CARBON 22K 5% 1/6W
	R030	1-247-163-00	CARBON 22K 5% 1/4W
	R031	1-247-163-00	CARBON 22K 5% 1/4W
	R032	1-249-433-11	CARBON 22K 5% 1/6W
	R033	1-249-433-11	CARBON 22K 5% 1/6W
	R034	1-249-433-11	CARBON 22K 5% 1/6W
	R035	1-249-433-11	CARBON 22K 5% 1/6W
	R037	1-249-417-11	CARBON 1K 5% 1/6W
	R038	1-249-422-11	CARBON 2.7K 5% 1/6W
	R039	1-249-405-11	CARBON 100 5% 1/6W
	R040	1-249-433-11	CARBON 22K 5% 1/6W
	R041	1-249-435-11	CARBON 33K 5% 1/6W
	R042	1-247-823-00	CARBON 470 5% 1/6W
	R043	1-247-823-00	CARBON 470 5% 1/6W
	R044	1-249-417-11	CARBON 1K 5% 1/6W
	R045	1-247-713-11	CARBON 1K 5% 1/4W
	R046	1-249-425-11	CARBON 4.7K 5% 1/6W
	R047	1-249-405-11	CARBON 100 5% 1/6W
	R048	1-249-441-11	CARBON 100K 5% 1/6W
	R049	1-216-464-11	METAL OXIDE 18K 5% 2W F
	R050	1-217-387-00	FUSIBLE 10 5% 1/4W F
	R052	1-247-713-11	CARBON 1K 5% 1/4W
	R053	1-247-883-00	CARBON 150K 5% 1/6W

Ref.No.	Part No.	Description
R054	1-247-815-00	CARBON 220 5% 1/6W
R056	1-247-859-00	CARBON 15K 5% 1/6W
R057	1-249-429-11	CARBON 10K 5% 1/6W
R060	1-247-819-00	CARBON 330 5% 1/6W
R061	1-249-433-11	CARBON 22K 5% 1/6W
R201	1-247-710-11	CARBON 560 5% 1/4W
R202	1-247-710-11	CARBON 560 5% 1/4W
R203	1-247-721-11	CARBON 4.7K 5% 1/4W
R204	1-247-721-11	CARBON 4.7K 5% 1/4W
R205	1-247-153-00	CARBON 8.2K 5% 1/4W
R206	1-247-869-00	CARBON 39K 5% 1/6W
R207	1-247-719-11	CARBON 3.3K 5% 1/4W
R208	1-249-423-11	CARBON 3.3K 5% 1/6W
R209	1-249-429-11	CARBON 10K 5% 1/6W
R210	1-249-417-11	CARBON 10K 5% 1/6W
R211	1-247-135-00	CARBON 1.5K 5% 1/4W
R213	1-247-895-00	CARBON 470K 5% 1/6W
R214	1-249-419-11	CARBON 1.5K 5% 1/6W
R216	1-249-429-11	CARBON 10K 5% 1/6W
R217	1-249-417-11	CARBON 1K 5% 1/6W
R218	1-247-887-00	CARBON 220K 5% 1/6W
R219	1-247-887-00	CARBON 220K 5% 1/6W
R220	1-247-104-00	CARBON 75 5% 1/4W
R221	1-247-708-11	CARBON 470 5% 1/4W
R222	1-247-873-00	CARBON 56K 5% 1/6W
R228	1-247-873-00	CARBON 56K 5% 1/6W
R229	1-249-422-11	CARBON 2.7K 5% 1/6W
R230	1-249-417-11	CARBON 1K 5% 1/6W
R231	1-247-821-00	CARBON 390 5% 1/6W
R232	1-247-688-11	CARBON 10 5% 1/4W
R233	1-247-823-00	CARBON 470 5% 1/6W
R234	1-249-440-11	CARBON 82K 5% 1/6W
R235	1-247-903-00	CARBON 1M 5% 1/6W
R236	1-249-429-11	CARBON 10K 5% 1/6W
R237	1-247-839-00	CARBON 2.2K 5% 1/6W
R238	1-249-420-11	CARBON 1.8K 5% 1/6W
R239	1-247-839-00	CARBON 2.2K 5% 1/6W
R240	1-249-429-11	CARBON 10K 5% 1/6W
R242	1-249-429-11	CARBON 10K 5% 1/6W
R243	1-249-432-11	CARBON 18K 5% 1/6W
R244	1-249-460-11	CARBON 15K 5% 1/4W
R245	1-249-437-11	CARBON 47K 5% 1/6W
R247	1-247-137-00	CARBON 1.8K 5% 1/4W
R248	1-247-713-11	CARBON 1K 5% 1/4W
R249	1-247-137-00	CARBON 1.8K 5% 1/4W
R251	1-247-815-00	CARBON 220 5% 1/6W
R252	1-249-405-11	CARBON 100 5% 1/6W
R253	1-249-405-11	CARBON 100 5% 1/6W
R254	1-249-405-11	CARBON 100 5% 1/6W
R255	1-247-719-11	CARBON 3.3K 5% 1/4W
R256	1-247-719-11	CARBON 3.3K 5% 1/4W
R257	1-247-104-00	CARBON 75 5% 1/4W
R278	1-217-387-00	FUSIBLE 10 5% 1/4W F

Remark	Ref.No.	Part No.	Description
	R279	1-217-387-00	FUSIBLE 10 5% 1/4W F
	R280	1-249-441-11	CARBON 100K 5% 1/6W
	R281	1-247-849-00	CARBON 5.6K 5% 1/6W
	R282	1-249-425-11	CARBON 4.7K 5% 1/6W
	R283	1-247-713-11	CARBON 1K 5% 1/4W
	R284	1-247-700-11	CARBON 100 5% 1/4W F
	R285	1-249-425-11	CARBON 4.7K 5% 1/6W
	R286	1-247-849-00	CARBON 5.6K 5% 1/6W
	R287	1-249-441-11	CARBON 100K 5% 1/6W
	R288	1-247-881-00	CARBON 120K 5% 1/6W
	R289	1-249-437-11	CARBON 47K 5% 1/6W
	R297	1-247-823-00	CARBON 470 5% 1/6W
	R298	1-247-823-00	CARBON 470 5% 1/6W
	R301	1-247-135-00	CARBON 1.5K 5% 1/4W
	R302	1-249-419-11	CARBON 1.5K 5% 1/6W
	R303	1-247-816-00	CARBON 240 5% 1/6W
	R304	1-249-429-11	CARBON 10K 5% 1/6W
	R305	1-247-849-00	CARBON 470 5% 1/6W
	R306	1-247-823-00	CARBON 470 5% 1/6W
	R307	1-249-415-11	CARBON 680 5% 1/6W
	R308	1-249-425-11	CARBON 4.7K 5% 1/6W
	R319	1-247-713-11	CARBON 1K 5% 1/4W
	R323	1-247-420-11	CARBON 1.8K 5% 1/6W
	R324	1-249-414-11	CARBON 560 5% 1/6W
	R325	1-247-707-11	CARBON 390 5% 1/4W
	R326	1-249-440-11	CARBON 82K 5% 1/6W
	R332	1-249-414-11	CARBON 560 5% 1/6W
	R333	1-247-849-00	CARBON 5.6K 5% 1/6W
	R334	1-247-151-00	CARBON 6.8K 5% 1/4W
	R335	1-249-437-11	CARBON 47K 5% 1/6W
	R336	1-249-429-11	CARBON 10K 5% 1/6W
	R337	1-249-429-11	CARBON 10K 5% 1/6W
	R338	1-249-417-11	CARBON 1K 5% 1/6W
	R339	1-249-417-11	CARBON 1K 5% 1/6W
	R340	1-247-821-00	CARBON 390 5% 1/6W
	R341	1-247-821-00	CARBON 390 5% 1/6W
	R342	1-247-903-00	CARBON 1M 5% 1/6W
	R343	1-249-441-11	CARBON 100K 5% 1/6W
	R344	1-247-149-00	CARBON 5.6K 5% 1/4W
	R345	1-247-882-00	CARBON 130K 5% 1/6W
	R347	1-249-414-11	CARBON 560 5% 1/6W
	R348	1-249-415-11	CARBON 680 5% 1/6W
	R349	1-247-849-00	CARBON 5.6K 5% 1/6W
	R350	1-247-853-00	CARBON 8.2K 5% 1/6W
	R351	1-249-433-11	CARBON 22K 5% 1/6W
	R352	1-249-420-11	CARBON 1.8K 5% 1/6W
	R353	1-249-423-11	CARBON 3.3K 5% 1/6W
	R354	1-247-883-00	CARBON 150K 5% 1/6W
	R356	1-247-857-00	CARBON 12K 5% 1/6W
	R357	1-247-849-00	CARBON 5.6K 5% 1/6W
	R358	1-249-432-11	CARBON 18K 5% 1/6W
	R359	1-247-859-00	CARBON 15K 5% 1/6W
	R360	1-246-517-00	CARBON 68K 5% 1/4W

D

Ref.No.	Part No.	Description		Remark	Ref.No.	Part No.	Description		Remark		
C315	1-123-381-00	ELECT	2.2MF	20%	50V	C522	1-123-318-00	ELECT	33MF	20%	16V
C316	1-108-622-91	MYLAR	0.0047MF	10%	100V	C523	1-108-431-00	MYLAR	0.068MF	10%	200V
C317	1-108-630-91	MYLAR	0.022MF	10%	100V	C524	1-123-162-00	ELECT	1MF	20%	50V
C318	1-131-345-00	TANTALUM	0.47MF	10%	35V	C525	1-123-362-00	ELECT	330MF	20%	50V
C319	1-123-356-00	ELECT	10MF	20%	16V	C527	1-123-360-00	ELECT	100MF	20%	50V
C320	1-123-586-00	ELECT	0.1MF	20%	50V	C528	1-123-321-00	ELECT	220MF	20%	16V
C321	1-131-345-00	TANTALUM	0.47MF	10%	35V	C529	1-123-333-00	ELECT	100MF	20%	16V
C322	1-131-345-00	TANTALUM	0.47MF	10%	35V	C530	1-106-359-00	MYLAR	0.0047MF	10%	200V
C323	1-102-110-00	CERAMIC	220PF	10%	50V	C531	1-123-356-00	ELECT	10MF	20%	50V
C324	1-102-110-00	CERAMIC	220PF	10%	50V	C532	1-106-190-00	MYLAR	0.0056MF	10%	100V
C325	1-136-173-00	FILM	0.47MF	5%	50V	C540	1-108-614-91	MYLAR	0.001MF	10%	100V
C326	1-136-173-00	FILM	0.47MF	5%	50V	C543	1-123-360-00	ELECT	100MF	20%	50V
C327	1-121-705-00	ELECT	2.2MF	30%	25V	C545	1-123-379-00	ELECT	0.47MF	20%	50V
C328	1-102-973-00	CERAMIC	100PF	5%	50V	C546	1-123-380-00	ELECT	1MF	20%	50V
C329	1-101-004-00	CERAMIC	0.01MF	5%	50V	C551	1-123-322-00	ELECT	330MF	20%	16V
C331	1-161-330-00	CERAMIC	0.01MF	30%	25V	C552	1-123-333-00	ELECT	100MF	20%	16V
C332	1-101-880-00	CERAMIC	47PF	5%	50V	C553	1-123-333-00	ELECT	100MF	20%	16V
C333	1-123-356-00	ELECT	10MF	20%	16V	C801	1-123-093-00	ELECT	22MF	20%	160V
C334	1-123-356-00	ELECT	10MF	20%	16V	C802	1-102-157-00	CERAMIC	560PF	10%	500V
C336	1-102-858-00	CERAMIC	10PF	0.5PF	50V	C803	1-102-327-11	CERAMIC	330PF	15%	1.5KV
C337	1-102-888-00	CERAMIC	150PF	5%	50V	C804	1-161-754-11	CERAMIC	0.001MF	10%	3KV
C338	1-102-884-00	CERAMIC	33PF	5%	50V	C805	1-108-423-00	MYLAR	0.015MF	10%	200V
C339	1-102-959-00	CERAMIC	22PF	5%	50V	C806	1-129-721-00	FILM	0.039MF	10%	630V
C340	1-102-945-00	CERAMIC	8PF	1PF	50V	C807	1-136-117-00	FILM	2MF	5%	200V
C341	1-102-947-00	CERAMIC	10PF	5%	50V	C808	1-136-053-00	FILM	1.2MF	5%	200V
C342	1-102-676-00	CERAMIC	68PF	5%	50V	C809	1-108-845-00	MYLAR	0.047MF	10%	50V
C343	1-102-973-00	CERAMIC	100PF	5%	50V	C810	1-106-196-00	MYLAR	0.01MF	10%	100V
C344	1-123-379-00	ELECT	0.47MF	20%	50V	C811	1-106-212-00	MYLAR	0.047MF	10%	100V
C346	1-123-333-00	ELECT	100MF	20%	16V	C812	1-102-223-00	CERAMIC	0.0047MF	10%	2KV
C347	1-108-622-91	MYLAR	0.0047MF	10%	100V	C813	1-106-210-00	MYLAR	0.039MF	10%	100V
C348	1-123-379-00	ELECT	0.47MF	20%	50V	C814	1-123-949-00	ELECT	33MF	20%	250V
C350	1-123-318-00	ELECT	33MF	20%	16V	C815	1-123-362-00	ELECT	330MF	20%	50V
C501	1-108-630-91	MYLAR	0.022MF	10%	100V	C816	1-102-030-00	CERAMIC	330PF	10%	500V
C502	1-136-171-00	FILM	0.33MF	5%	50V	C818	1-130-894-00	FILM	0.022MF	3%	1.2KV
C503	1-136-171-00	FILM	0.33MF	5%	50V	C819	1-129-711-51	FILM	0.0056MF	10%	630V
C504	1-102-108-00	CERAMIC	150PF	10%	50V	C821	1-102-038-00	CERAMIC	0.001MF		500V
C505	1-123-380-00	ELECT	1MF	20%	50V	C822	1-102-038-00	CERAMIC	0.001MF		500V
C506	1-123-330-00	ELECT	22MF	20%	16V	C824	1-108-630-91	MYLAR	0.022MF	10%	100V
C507	1-106-224-00	MYLAR	0.15MF	10%	100V	C825	1-136-184-00	MYLAR	0.68MF	10%	250V
C508	1-123-356-00	ELECT	10MF	20%	16V	C828	1-102-114-00	CERAMIC	470PF	10%	50V
C509	1-123-369-00	ELECT	4.7MF	20%	25V	C830	1-123-380-00	ELECT	1MF	20%	50V
C510	1-123-323-00	ELECT	470MF	20%	16V						
C511	1-123-379-00	ELECT	0.47MF	20%	50V						
C512	1-106-220-00	MYLAR	0.1MF	10%	100V						
C513	1-130-023-00	FILM	0.0027MF	5%	50V						
C514	1-123-332-00	ELECT	47MF	20%	16V						
C515	1-106-220-00	MYLAR	0.1MF	10%	100V						
C516	1-123-357-00	ELECT	22MF	20%	50V						
C517	1-102-030-00	CERAMIC	330PF	10%	500V						
C518	1-129-743-00	FILM	0.022MF	10%	400V						
C519	1-123-931-00	ELECT	3.3MF	20%	160V						
C520	1-106-182-00	MYLAR	0.0027MF	10%	100V						
C521	1-102-157-00	CERAMIC	560PF	10%	500V						
										</	

Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark
D4	*1-564-885-11	PLUG, CONNECTOR 8P		D223	8-719-101-76	DIODE RD10E-L2	
D5	*1-508-765-00	3P PLUG (M)		D224	8-719-101-76	DIODE RD10E-L2	
D6	*1-560-123-00	PLUG, CONNECTOR (2.5MM) 3P		D271	8-719-911-55	DIODE U05G	
D7	*1-564-883-11	PLUG, CONNECTOR 6P		D303	8-719-911-19	DIODE 1SS119	
D8	*1-564-889-11	PLUG, CONNECTOR 12P		D304	8-719-911-19	DIODE 1SS119	
D10	*1-508-766-00	4P PLUG (M)		D305	8-719-911-19	DIODE 1SS119	
D12	*1-508-786-00	2P PLUG (M)		D306	8-719-911-19	DIODE 1SS119	
D14	*1-564-884-31	PLUG, CONNECTOR 7P		D307	8-719-911-19	DIODE 1SS119	
D15	*1-560-290-00	PLUG, CONNECTOR (2.5MM PITCH)		D308	8-719-911-19	DIODE 1SS119	
D16	*1-560-290-00	PLUG, CONNECTOR (2.5MM PITCH)		D309	8-719-911-19	DIODE 1SS119	
D17	*1-560-126-00	PLUG, CONNECTOR (2.5MM PITCH)		D312	8-719-911-19	DIODE 1SS119	
D18	*1-560-126-00	PLUG, CONNECTOR (2.5MM) 6P		D501	8-719-911-19	DIODE 1SS119	
D19	*1-564-346-00	CONNECTOR, BOARD TO BOARD 18P		D503	8-719-924-06	DIODE ERC24-06S	
D20	*1-564-346-00	CONNECTOR, BOARD TO BOARD 18P		D504	8-719-924-06	DIODE ERC24-06S	
D21	*1-560-123-00	PLUG, CONNECTOR (2.5MM PITCH)		D505	8-719-924-06	DIODE ERC24-06S	
D22	*1-560-127-00	PLUG, CONNECTOR (2.5MM PITCH)		D506	8-719-911-19	DIODE 1SS119	
D23	*1-560-126-00	PLUG, CONNECTOR (2.5MM PITCH)		D507	8-719-924-06	DIODE ERC24-06S	
D24	*1-508-784-00	1P PLUG		D551	8-719-911-19	DIODE 1SS119	
D27	*1-560-290-00	PLUG, CONNECTOR (2.5MM PITCH)		D552	8-719-911-19	DIODE 1SS119	
D28	*1-508-784-00	1P PLUG		D553	8-719-924-06	DIODE ERC24-06S	
D30	*1-564-879-11	PLUG, CONNECTOR 2P		D554	8-719-924-06	DIODE ERC24-06S	
D32	*1-508-784-00	1P PLUG		D555	8-719-911-19	DIODE 1SS119	
DY1	*1-508-765-00	3P PLUG (M)		D801	8-719-900-26	DIODE ERD29-08J	
DY2	*1-508-765-00	3P PLUG (M)		D802	8-719-300-65	DIODE ES1F	
DY3	*1-508-766-00	4P PLUG (M)		D803	8-719-924-06	DIODE ERC24-06S	
		TRIMMER		D804	8-719-924-06	DIODE ERC24-06S	
CV301	1-141-181-11	CAP, TRIMMER		D805	8-719-931-13	DIODE E0801-13	
		DIODE		D806	8-719-305-15	DIODE GH3F	
				D807	8-719-305-15	DIODE GH3F	
						DELAY LINE	
D001	8-719-911-19	DIODE 1SS119		DL301	1-415-427-11	DELAY LINE, Y	
D002	8-719-911-19	DIODE 1SS119		DL302	1-415-122-31	DELAY LINE, 1H (PAL)	
D003	8-719-911-19	DIODE 1SS119					
D004	8-719-911-19	DIODE 1SS119 (KV-27XSC ONLY)					
D005	8-759-157-40	IC UPC574J				IC	
D006	8-719-100-98	DIODE RD30E-B2		IC001	8-759-603-67	IC CX523-117P	
D008	8-719-911-19	DIODE 1SS119		IC002	8-759-600-92	IC M58657P	
D010	8-719-911-19	DIODE 1SS119		IC201	8-759-914-76	IC CX20199	
D061	8-719-100-35	DIODE RD5.6E-B2		IC202	8-752-006-10	IC CX20061	
D062	8-719-911-19	DIODE 1SS119		IC251	8-749-943-62	IC STK-4362	
D201	8-719-911-19	DIODE 1SS119			*4-368-684-01	SPRING (L);IC251	
D205	8-719-100-44	DIODE RD7.5E-B2		IC301	8-759-927-67	IC TDA3562A-N5	
D206	8-719-911-19	DIODE 1SS119		IC551	8-759-915-46	IC TDA2579	
D212	8-719-911-19	DIODE 1SS119			4-375-717-01	HEAT SINK, IC;IC551	
D213	8-719-911-19	DIODE 1SS119					
						MODULE	
D214	8-719-911-19	DIODE 1SS119		IC302	1-235-534-11	CONTROL MODULE, PICTURE	
D215	8-719-911-19	DIODE 1SS119					
D216	8-719-911-19	DIODE 1SS119					
D217	8-719-911-19	DIODE 1SS119				COIL	
D218	8-719-911-19	DIODE 1SS119					
D219	8-719-911-19	DIODE 1SS119		L001	1-408-425-00	MICRO INDUCTOR 220UH	
D221	8-719-101-76	DIODE RD10E-L2		L251	1-459-407-00	COIL, FERRITE CHOKE	
D222	8-719-101-76	DIODE RD10E-L2		L252	1-459-407-00	COIL, FERRITE CHOKE	
				L301	1-404-495-00	COIL	
				L302	1-408-412-00	MICRO INDUCTOR 18UH	

H2

(KV27XSTA only)

Ref.No.	Part No.	Description	Remark
<u>DIODE</u>			
LED401	8-719-908-08	DIODE SL-1274	
	*1-526-638-00	SOCKET, IC (9P); LED401	
LED402	8-719-903-11	DIODE GL-9PR24	
LED404	8-719-903-11	DIODE GL-9PR24	
LED405	8-719-903-11	DIODE GL-9PR24	
LED406	8-719-903-11	DIODE GL-9PR24	
<u>RESISTOR</u>			
R407	1-247-813-00	CARBON 180 5% 1/6W	
R412	1-247-813-00	CARBON 180 5% 1/6W	

<u>MISCELLANEOUS</u>			

	1-246-521-00	RES, CARBON 100K	
Δ	1-451-255-31	DEFLECTION YOKE (SY-164)	
	1-452-032-00	MAGNET, DISK; 10MM Ø	
	1-452-094-00	MAGNET, ROTATABLE DISK; 15MM Ø	
	1-452-146-21	MAGNET, BMC	
Δ	1-452-391-21	NECK ASSY, CRT (NA305)	
Δ	1-536-817-31	TERMINAL BOARD ASSY, ANTENNA	
Δ	1-551-270-11	CORD, POWER	
L901	Δ 1-426-278-11	COIL, DEMAGNETIZATION	
RV901	Δ 1-228-544-11	RESISTOR ASSY, HIGH-VOLTAGE	
RV902	Δ 1-237-280-11	RESISTOR ASSY, HIGH-VOLTAGE	
S901	Δ 1-554-762-41	SWITCH, PUSH (AC POWER)(1 KEY)	
SP901	1-503-642-11	SPEAKER (R)	
SP902	1-503-642-11	SPEAKER (L)	
V901	Δ 8-736-653-05	CRT (A64JKJ60X)	

<u>ACCESSORIES AND PACKING MATERIALS</u>			

Part No.	Description	Remark	
A-1470-758-A	COMMANDER ASSY (RM-635)		
3-701-627-00	BAG, POLYETHYLENE		
4-337-844-00	BAG, PROTECTION		
4-482-288-41	MANUAL, INSTRUCTION		

*A-1296-105-A A BOARD, SUB COMPLETE

*4-368-692-03 CASE (MAIN), SHIELD
*4-368-693-02 CASE (UPPER LID), SHIELD

Num. Ref.	Num. Parte	Description	Osservazione	Num. Ref.	Num. Parte	Descrizione	Osservazione
*4-368-694-02 CASE (BOTTOM LID), SHIELD				C151	1-101-004-00	CERAMIC 0.01MF	50V
<u>CONNECTOR</u>				C152	1-101-004-00	CERAMIC 0.01MF	50V
A1	*1-564-880-31	PLUG, CONNECTOR 3P		C153	1-123-356-00	ELECT 10MF	20% 16V
A2	*1-560-126-00	PLUG, CONNECTOR (2.5MM) 6P		C154	1-101-004-00	CERAMIC 0.01MF	50V
A3	*1-564-889-11	PLUG, CONNECTOR 12P		C155	1-123-332-00	ELECT 47MF	20% 16V
<u>CAPACITOR</u>				C156	1-123-306-00	ELECT 47MF	20% 10V
C102	1-123-356-00	ELECT 10MF	20% 16V	C157	1-123-306-00	ELECT 47MF	20% 10V
C104	1-123-356-00	ELECT 10MF	20% 16V	C158	1-123-379-00	ELECT 0.47MF	20% 50V
C105	1-123-356-00	ELECT 10MF	20% 16V	C159	1-102-816-00	CERAMIC 120PF	5% 50V
C106	1-123-323-00	ELECT 470MF	20% 16V	C160	1-102-125-00	CERAMIC 0.0047MF	10% 50V
C107	1-123-330-00	ELECT 22MF	20% 16V	C164	1-108-620-91	MYLAR 0.0033MF	10% 100V
C108	1-136-163-00	FILM 0.068MF	5% 50V	C165	1-108-620-91	MYLAR 0.0033MF	10% 100V
C109	1-136-163-00	FILM 0.068MF	5% 50V	C167	1-108-620-91	MYLAR 0.0033MF	10% 100V
C110	1-102-963-00	CERAMIC 33PF	5% 50V	C168	1-108-620-91	MYLAR 0.0033MF	10% 100V
C111	1-123-318-00	ELECT 33MF	20% 16V	C169	1-123-356-00	ELECT 10MF	20% 16V
C112	1-102-527-00	CERAMIC 82PF	5% 50V	C170	1-123-356-00	ELECT 10MF	20% 16V
C113	1-102-510-00	CERAMIC 12PF	5% 50V	C171	1-123-318-00	ELECT 33MF	20% 16V
C115	1-102-852-00	CERAMIC 47PF	5% 50V	C172	1-123-379-00	ELECT 0.47MF	20% 50V
C116	1-102-125-00	CERAMIC 0.0047MF	10% 50V	C173	1-123-379-00	ELECT 0.47MF	20% 50V
C117	1-102-125-00	CERAMIC 0.0047MF	10% 50V	C174	1-110-190-81	MYLAR 0.01MF	10% 400V
C118	1-102-125-00	CERAMIC 0.0047MF	10% 50V	C175	1-110-190-81	MYLAR 0.01MF	10% 400V
C119	1-108-603-00	MYLAR 0.1MF	5% 50V	C176	1-123-380-00	ELECT 1MF	20% 50V
C120	1-102-125-00	CERAMIC 0.0047MF	10% 50V	C177	1-123-380-00	ELECT 1MF	20% 50V
C122	1-123-330-00	ELECT 22MF	20% 16V	C179	1-123-369-00	ELECT 4.7MF	20% 25V
C123	1-102-108-00	CERAMIC 150PF	10% 50V	C180	1-108-620-91	MYLAR 0.0033MF	10% 100V
C124	1-104-069-00	POLYSTYRENE 470PF	5% 50V	C181	1-123-318-00	ELECT 33MF	20% 16V
C125	1-101-361-00	CERAMIC 150PF	5% 50V	C182	1-123-307-00	ELECT 100MF	20% 10V
C126	1-123-318-00	ELECT 33MF	20% 16V	C183	1-101-361-00	CERAMIC 150PF	5% 50V
C127	1-102-125-00	CERAMIC 0.0047MF	10% 50V	C184	1-102-973-00	CERAMIC 100PF	5% 50V
C128	1-101-004-00	CERAMIC 0.01MF	50V	C186	1-102-121-00	CERAMIC 0.0022MF	10% 50V
C129	1-101-004-00	CERAMIC 0.01MF	50V	C188	1-102-125-00	CERAMIC 0.0047MF	10% 50V
C130	1-102-125-00	CERAMIC 0.0047MF	10% 50V	C189	1-101-006-00	CERAMIC 0.047MF	50V
C131	1-123-381-00	ELECT 2.2MF	20% 50V	C190	1-106-220-00	MYLAR 0.1MF	10% 100V
C132	1-102-125-00	CERAMIC 0.0047MF	10% 50V	<u>FILTER</u>			
C133	1-102-125-00	CERAMIC 0.0047MF	10% 50V	CD151	1-404-501-00	DISCRIMINATOR, CERAMIC	
C134	1-102-125-00	CERAMIC 0.0047MF	10% 50V	CF101	1-527-840-00	FILTER, CERAMIC	
C135	1-102-525-00	CERAMIC 68PF	5% 50V	CF102	1-404-134-00	TRAP, CERAMIC (5.5MHZ)	
C136	1-102-525-00	CERAMIC 68PF	5% 50V	CF151	1-527-839-00	FILTER, CERAMIC	
C137	1-102-125-00	CERAMIC 0.0047MF	10% 50V	<u>DIODE</u>			
C138	1-123-380-00	ELECT 1MF	20% 50V	D102	8-719-911-19	DIODE 1SS119	
C139	1-102-125-00	CERAMIC 0.0047MF	10% 50V	D103	8-719-102-71	DIODE R05.6E-N2	
C140	1-102-125-00	CERAMIC 0.0047MF	10% 50V	D104	8-719-911-19	DIODE 1SS119	
C141	1-123-318-00	ELECT 33MF	20% 16V	D105	8-719-911-19	DIODE 1SS119	
C142	1-102-525-00	CERAMIC 68PF	5% 50V	D151	8-719-911-19	DIODE 1SS119	
C143	1-101-004-00	CERAMIC 0.01MF	50V	D152	8-719-911-19	DIODE 1SS119	
C144	1-123-286-00	ELECT 0.33MF	20% 50V	D153	8-719-911-19	DIODE 1SS119	
C145	1-102-961-00	CERAMIC 27PF	5% 50V	D154	8-719-911-19	DIODE 1SS119	
C146	1-123-380-00	ELECT 1MF	20% 50V	D170	8-719-911-19	DIODE 1SS119	
C147	1-130-072-00	FILM 0.022MF	2% 100V	D171	8-719-911-19	DIODE 1SS119	
C148	1-110-186-81	MYLAR 0.0047MF	10% 400V				
C150	1-102-520-00	CERAMIC 39PF	5% 50V				

D

D

J1

H1

H2

Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark
R362	1-247-717-11	CARBON	2.2K 5% 1/4W	R537	1-249-441-11	CARBON	100K 5% 1/6W
R364	1-247-839-00	CARBON	2.2K 5% 1/6W	R538	1-247-753-11	CARBON	1.2K 5% 1/2W F
R365	1-247-857-00	CARBON	12K 5% 1/6W	R539	1-249-440-11	CARBON	82K 5% 1/6W
R366	1-247-717-11	CARBON	2.2K 5% 1/4W	R540	1-246-507-00	CARBON	27K 5% 1/4W
R367	1-247-815-00	CARBON	220 5% 1/6W	R541	1-247-823-00	CARBON	470 5% 1/6W
R368	1-247-815-00	CARBON	220 5% 1/6W	R542	1-216-435-11	METAL OXIDE	2.7K 5% 1W F
R369	1-247-815-00	CARBON	220 5% 1/6W	R543	1-247-903-00	CARBON	1M 5% 1/6W
R370	1-247-708-11	CARBON	470 5% 1/4W	R544	1-202-467-92	SOL ID	3.3M 10% 1/4W
R371	1-249-405-11	CARBON	100 5% 1/6W	R547	1-212-990-00	FUSIBLE	220 5% 1/2W F
R373	1-247-713-11	CARBON	1K 5% 1/4W	R548	1-216-350-11	METAL OXIDE	1.2 5% 1W F
R376	1-246-507-00	CARBON	27K 5% 1/4W	R549	1-247-033-00	CARBON	100 5% 1/8W F
R377	1-246-507-00	CARBON	27K 5% 1/4W	R550	1-246-537-00	CARBON	470K 5% 1/4W
R378	1-249-432-11	CARBON	18K 5% 1/6W	R551	1-217-383-00	FUSIBLE	4.7 5% 1/4W F
R379	1-247-864-00	CARBON	24K 5% 1/6W	R552	1-217-383-00	FUSIBLE	4.7 5% 1/4W F
R380	1-249-440-11	CARBON	82K 5% 1/6W	R553	1-246-979-00	CARBON	1.2 5% 1/8W F
R381	1-249-417-11	CARBON	1K 5% 1/6W	R554	1-249-425-11	CARBON	4.7K 5% 1/6W
R382	1-249-417-11	CARBON	1K 5% 1/6W	R555	1-247-839-00	CARBON	2.2K 5% 1/6W
R383	1-249-417-11	CARBON	1K 5% 1/6W	R556	1-216-350-11	METAL OXIDE	1.2 5% 1W F
R385	1-249-422-11	CARBON	2.7K 5% 1/6W	R557	1-247-819-00	CARBON	330 5% 1/6W
R386	1-249-422-11	CARBON	2.7K 5% 1/6W	R558	1-247-883-00	CARBON	150K 5% 1/6W
R387	1-249-422-11	CARBON	2.7K 5% 1/6W	R559	1-247-719-11	CARBON	3.3K 5% 1/4W
R390	1-247-161-00	CARBON	18K 5% 1/4W	R560	1-247-839-00	CARBON	2.2K 5% 1/6W
R504	1-249-422-11	CARBON	2.7K 5% 1/6W	R571	1-247-895-00	CARBON	470K 5% 1/6W
R505	1-249-423-11	CARBON	3.3K 5% 1/6W	R572	1-249-441-11	CARBON	100K 5% 1/6W
R506	1-247-833-00	CARBON	1.2K 5% 1/6W	R573	1-247-903-00	CARBON	1M 5% 1/6W
R507	1-249-417-11	CARBON	1K 5% 1/6W	R574	1-247-903-00	CARBON	1M 5% 1/6W
R508	1-215-461-00	METAL	47K 1% 1/6W	R575	1-247-177-00	CARBON	82K 5% 1/4W
R509	1-215-477-00	METAL	220K 1% 1/6W	R578	1-247-704-11	CARBON	220 5% 1/4W
R510	1-247-851-00	CARBON	6.8K 5% 1/6W	R593	1-249-425-11	CARBON	4.7K 5% 1/6W
R511	1-247-805-00	CARBON	82 5% 1/6W	R594	1-249-433-11	CARBON	22K 5% 1/6W
R512	1-247-829-00	CARBON	820 5% 1/6W	R595	1-247-859-00	CARBON	15K 5% 1/6W
R513	1-247-857-00	CARBON	12K 5% 1/6W	R596	1-249-423-11	CARBON	3.3K 5% 1/6W
R514	1-249-417-11	CARBON	1K 5% 1/6W	R597	1-247-719-11	CARBON	3.3K 5% 1/4W
R515	1-247-700-11	CARBON	100 5% 1/4W	R598	1-247-849-00	CARBON	5.6K 5% 1/6W
R516	1-247-717-11	CARBON	2.2K 5% 1/4W	R599	1-247-815-00	CARBON	220 5% 1/6W
R517	1-246-511-00	CARBON	39K 5% 1/4W	R800	1-215-886-11	METAL OXIDE	100 5% 2W F
R520	1-214-765-00	METAL	33K 1% 1/4W	R801	1-216-345-11	METAL OXIDE	0.47 5% 1W F
R521	1-216-464-11	METAL OXIDE	18K 5% 2W F	R802	1-247-137-00	CARBON	1.8K 5% 1/4W
R522	1-247-901-00	CARBON	820K 5% 1/6W	R803	1-247-803-00	CARBON	68 5% 1/6W
R523	1-247-033-00	CARBON	100 5% 1/8W F	R804	1-215-871-11	METAL OXIDE	2.2K 5% 1W F
R524	1-215-869-11	METAL OXIDE	1K 5% 1W F	R805	1-215-866-11	METAL OXIDE	330 5% 1W F
R525	1-246-985-00	CARBON	33 5% 1/8W F	R806	1-202-838-00	SOL ID	100K 10% 1/2W
R526	1-247-839-00	CARBON	2.2K 5% 1/6W	R807	1-202-824-00	SOL ID	3.3K 10% 1/2W
R527	1-246-982-00	CARBON	10 5% 1/8W F	R808	1-202-826-00	SOL ID	4.7K 10% 1/2W
R528	1-247-161-00	CARBON	18K 5% 1/4W	R809	1-244-925-00	CARBON	150K 5% 1/2W
R529	1-247-711-11	CARBON	680 5% 1/4W	R810	1-246-979-00	CARBON	1.2 5% 1/8W F
R530	1-247-892-00	CARBON	360K 5% 1/6W	R811	1-249-448-11	CARBON	1.2 5% 1/4W F
R531	1-247-707-11	CARBON	390 5% 1/4W	R812	1-247-270-00	CARBON	18K 5% 1/2W
R532	1-247-719-11	CARBON	3.3K 5% 1/4W	R813	1-215-883-11	METAL OXIDE	33 5% 2W F
R533	1-247-859-00	CARBON	15K 5% 1/6W	R814	1-246-537-00	CARBON	470K 5% 1/4W
R534	1-247-787-00	CARBON	15 5% 1/6W	R817	1-216-379-11	METAL OXIDE	6.8 5% 2W F
R535	1-247-783-00	CARBON	10 5% 1/6W	R820	1-215-884-11	METAL OXIDE	47 5% 2W F
R536	1-216-354-11	METAL OXIDE	2.7 5% 1W F	R821	1-215-870-11	METAL OXIDE	1.5K 5% 1W F

Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark
R825	1-207-678-00	WIREWOUND	10 10% 5W F			DIODE	
R826	1-207-678-00	WIREWOUND	10 10% 5W F	D401	8-719-911-19	DIODE 1SS119	
		VARIABLE RESISTOR		D402	8-719-911-19	DIODE 1SS119	
RV301	1-228-720-00	RES, ADJ, CERAMIC CARBON 1K		D403	8-719-911-19	DIODE 1SS119	
RV302	1-228-724-00	RES, ADJ, CERAMIC CARBON 10K		D404	8-719-911-19	DIODE 1SS119	
RV303	1-228-725-00	RES, ADJ, CERAMIC CARBON 22K		D405	8-719-911-19	DIODE 1SS119	
RV501	1-226-776-00	RES, ADJ, METAL GLAZE 220K		D406	8-719-911-19	DIODE 1SS119	
RV502	1-226-775-00	RES, ADJ, METAL GLAZE 100K		D407	8-719-911-19	DIODE 1SS119	
RV503	1-230-522-11	RES, ADJ, METAL GLAZE 4.7K		D409	8-719-911-19	DIODE 1SS119	
RV558	1-228-720-00	RES, ADJ, CERAMIC CARBON 1K				CONNECTOR	
RV558	1-228-720-00	RES, ADJ, CERAMIC CARBON 1K		H4	*1-564-457-11	PLUG, CONNECTOR (2.5MM) 9P	
		SPARK GAP		H5	*1-564-454-31	PLUG, CONNECTOR (2.5MM) 6P	
SG801	1-519-063-XX	DISCHARGING GAP		H6	*1-564-897-11	PLUG, CONNECTOR 8P	
		TRANSFORMER				RESISTOR	
T301	1-426-121-00	DAT		R401	1-249-425-11	CARBON	4.7K 5% 1/6W
T801	1-437-090-11	HOT		R402	1-249-425-11	CARBON	4.7K 5% 1/6W
T802	1-439-332-42	TRANSFORMER ASSY, FLYBACK		R405	1-247-849-00	CARBON	5.6K 5% 1/6W
T803	1-413-059-00	TRANSFORMER, FERRITE (DFT)		R406	1-247-849-00	CARBON	5.6K 5% 1/6W
		THERMISTOR		R418	1-247-839-00	CARBON	2.2K 5% 1/6W
TH501	1-806-213-00	THERMISTOR		R419	1-249-420-11	CARBON	1.8K 5% 1/6W
		CRYSTAL				VARIABLE RESISTOR	
X301	1-527-789-00	VINRATOR, CRYSTAL		RV401	1-228-578-00	RES, VAR, CARBON 10K	
		*****		RV402	1-228-578-00	RES, VAR, CARBON 10K	
*1-618-883-11	J1 BOARD	*****		RV403	1-228-578-00	RES, VAR, CARBON 10K	
		CONNECTOR		RV404	1-228-578-00	RES, VAR, CARBON 10K	
CN901	1-507-657-00	JACK (LARGE TYPE)				SWITCH	
J1	*1-564-883-11	PLUG, CONNECTOR 6P		SW401	1-554-118-00	SWITCH, PUSH (1 KEY)	
		RESISTOR		SW407	1-553-329-00	SWITCH, PUSH (MONO KEY)	
R901	1-247-708-11	CARBON	470 5% 1/4W	SW408	1-553-329-00	SWITCH, PUSH (MONO KEY)	
R902	1-247-708-11	CARBON	470 5% 1/4W	SW411	1-553-329-00	SWITCH, PUSH (MONO KEY)	
		*****		SW412	1-553-329-00	SWITCH, PUSH (MONO KEY)	
*1-619-358-11	H1 BOARD	*****		SW413	1-553-329-00	SWITCH, PUSH (MONO KEY)	
*1-506-908-11	PLUG, CONNECTOR (2.5MM) 14P			SW414	1-553-329-00	SWITCH, PUSH (MONO KEY)	
		CAPACITOR		SW415	1-553-329-00	SWITCH, PUSH (MONO KEY)	
C401	1-123-617-00	ELECT	10MF 20% 16V	SW416	1-553-329-00	SWITCH, PUSH (MONO KEY)	
C403	1-123-616-00	ELECT	4.7MF 20% 25V	SW417	1-553-329-00	SWITCH, PUSH (MONO KEY)	
		*****		SW418	1-553-329-00	SWITCH, PUSH (MONO KEY)	
		*****		SW419	1-553-329-00	SWITCH, PUSH (MONO KEY)	
		*****				*****	
		*****		*1-619-359-11	H2 BOARD	*****	
		*****				*****	
		*****		*1-506-908-11	PLUG, CONNECTOR (2.5MM) 14P		
		*****		*4-373-201-01	COVER, LED HOLDER		
		*****		*4-373-202-01	HOLDER, LED		

(KV27XSTA only)

*A-1325-030-A V BOARD, COMPLETE

*4-371-102-01 CASE (MAIN), SHIELD, AI
*4-371-103-01 CASE (UPPER LID), SHIELD, AI
*4-371-104-01 CASE (BOTTOM LID), SHIELD, AI

CAPACITOR

C001	1-123-307-00	ELECT	100MF	20%	10V
C002	1-123-332-00	ELECT	47MF	20%	16V
C003	1-123-309-00	ELECT	330MF	20%	6.3V
C004	1-123-332-00	ELECT	47MF	20%	16V
C005	1-123-308-00	ELECT	220MF	20%	6.3V
C006	1-123-321-00	ELECT	220MF	20%	16V
C007	1-110-175-81	MYLAR	0.1MF	10%	100V
C008	1-102-951-00	CERAMIC	15PF	5%	50V
C009	1-102-074-00	CERAMIC	0.001MF	10%	50V
C010	1-102-824-00	CERAMIC	470PF	5%	50V
C011	1-110-182-81	MYLAR	0.022MF	10%	250V
C012	1-102-980-00	CERAMIC	270PF	5%	50V
C013	1-102-973-00	CERAMIC	100PF	5%	50V
C014	1-102-851-00	CERAMIC	15PF	5%	50V
C015	1-102-883-00	CERAMIC	27PF	5%	50V
C016	1-110-190-81	MYLAR	0.01MF	10%	400V
C017	1-110-171-81	MYLAR	0.047MF	10%	100V
C018	1-102-953-00	CERAMIC	18PF	5%	50V
C019	1-110-171-81	MYLAR	0.047MF	10%	100V
C020	1-102-978-00	CERAMIC	220PF	5%	50V
C021	1-110-173-81	MYLAR	0.068MF	10%	100V
C022	1-102-963-00	CERAMIC	33PF	5%	50V
C023	1-102-963-00	CERAMIC	33PF	5%	50V
C024	1-136-177-00	FILM	1MF	5%	50V
C025	1-123-298-00	ELECT	470MF	20%	6.3V



Num. Ref.	Num. Parte	Descrizione	Osservazione
C026	1-102-973-00	CERAMIC 100PF	5% 50V
C037	1-110-175-81	MYLAR 0.1MF	10% 100V
C040	1-136-177-00	FILM 1MF	5% 50V
C041	1-110-175-81	MYLAR 0.1MF	10% 100V
C042	1-102-820-00	CERAMIC 330PF	5% 50V
C043	1-123-308-00	ELECT 220MF	20% 6.3V
C044	1-110-175-81	MYLAR 0.1MF	10% 100V
C045	1-102-116-00	CERAMIC 680PF	10% 50V
C046	1-123-356-00	ELECT 10MF	20% 16V
C049	1-101-361-00	CERAMIC 150PF	10% 50V
C050	1-101-361-00	CERAMIC 150PF	10% 50V
TRIMMER			
CT001	1-141-181-11	CAP, TRIMMER	
DIODE			
D001	8-719-911-19	DIODE 1SS119	
D002	8-719-100-35	DIODE RD5.6E-82	
D003	8-719-100-68	DIODE RD13E-82	
D004	8-719-101-41	DIODE RD3.9E-42	
D005	8-719-109-88	DIODE RD5.6ES-81	
D006	8-719-911-19	DIODE 1SS119	
D007	8-719-911-19	DIODE 1SS119	
D008	8-719-911-19	DIODE 1SS119	
D011	8-719-911-19	DIODE 1SS119	
D012	8-719-911-19	DIODE 1SS119	
D013	8-719-109-88	DIODE RD5.6ES-81	
IC			
IC001	8-759-918-54	IC SAA5230	
IC002	8-759-924-41	IC SAA5240B	
	*1-526-722-00	SOCKET, IC 40P; IC002	
IC003	8-759-206-27	IC TC5564PL-15	
IC004	8-759-108-76	IC CX526-050	
COIL			
L001	1-408-411-00	MICRO INDUCTOR 15UH	
TRANSISTOR			
Q001	8-729-109-53	TRANSISTOR 2SD1795A	
Q002	8-729-178-54	TRANSISTOR 2SC2785	
Q003	8-729-177-43	TRANSISTOR 2SD1774	
Q004	8-729-117-54	TRANSISTOR 2SA1175	
Q005	8-729-900-89	TRANSISTOR DTC144ES	
Q006	8-729-117-54	TRANSISTOR 2SA1175	
Q007	8-729-178-54	TRANSISTOR 2SC2785	
Q008	8-729-178-54	TRANSISTOR 2SC2785	
Q009	8-729-900-89	TRANSISTOR DTC144ES	
Q010	8-729-117-54	TRANSISTOR 2SA1175	
Q011	8-729-117-54	TRANSISTOR 2SA1175	
Q012	8-729-117-54	TRANSISTOR 2SA1175	



Num. Ref.	Num. Parte	Descrizione	Osservazione	Num. Ref.	Num. Parte	Descrizione	Osservazione
RESISTOR							
R001	1-215-867-00	METAL OXIDE	470 5% 1W F	X002	1-567-495-11	OSCILLATOR, CRYSTAL	
R002	1-215-762-91	METAL	10K 5% 1/6W	X003	1-567-192-11	OSCILLATOR, CERAMIC	
R003	1-215-778-91	METAL	47K 5% 1/6W	*****			
R004	1-247-745-11	CARBON	330 5% 1/2W				
R005	1-215-736-91	METAL	820 5% 1/6W				
R006	1-215-754-91	METAL	4.7K 5% 1/6W				
R007	1-215-726-91	METAL	330 5% 1/6W				
R008	1-215-780-91	METAL	56K 5% 1/6W				
R009	1-215-738-91	METAL	1K 5% 1/6W				
R010	1-215-770-91	METAL	22K 5% 1/6W				
R011	1-215-738-91	METAL	1K 5% 1/6W				
R012	1-215-762-91	METAL	10K 5% 1/6W				
R014	1-215-738-91	METAL	1K 5% 1/6W				
R015	1-215-738-91	METAL	1K 5% 1/6W				
R016	1-215-132-00	METAL	150 5% 1/4W				
R017	1-215-132-00	METAL	150 5% 1/4W				
R018	1-215-132-00	METAL	150 5% 1/4W				
R019	1-215-132-00	METAL	150 5% 1/4W				
R020	1-215-716-91	METAL	120 5% 1/6W				
R021	1-215-716-91	METAL	120 5% 1/6W				
R022	1-215-716-91	METAL	120 5% 1/6W				
R023	1-215-776-91	METAL	39K 5% 1/6W				
R024	1-215-756-91	METAL	5.6K 5% 1/6W				
R025	1-215-746-91	METAL	2.2K 5% 1/6W				
R040	1-215-714-91	METAL	100 5% 1/6W				
R044	1-217-376-00	FUSIBLE	1.2 5% 1/4W F				
R046	1-215-726-91	METAL	330 5% 1/6W				
R047	1-215-762-91	METAL	10K 5% 1/6W				
R048	1-215-764-91	METAL	12K 5% 1/6W				
R049	1-215-690-91	METAL	10 5% 1/6W				
R052	1-215-738-91	METAL	1K 5% 1/6W				
R065	1-215-738-91	METAL	1K 5% 1/6W				
VARIABLE RESISTOR							
RV001	1-230-631-11	RES, ADJ, CARBON 22K					
RV002	1-224-247-XX	RES, ADJ, METAL GLAZE 100					
CONNECTOR							
V1	*1-560-124-00	PLUG, CONNECTOR (2.5MM PITCH)					
V2	*1-560-124-00	PLUG, CONNECTOR (2.5MM PITCH)					
V4	*1-560-124-00	PLUG, CONNECTOR (2.5MM PITCH)					
V5	*1-560-124-00	PLUG, CONNECTOR (2.5MM PITCH)					
V6	*1-508-784-00	1P PLUG					
V9	*1-560-126-00	PLUG, CONNECTOR (2.5MM PITCH)					
V10	*1-508-784-00	1P PLUG					
V11	*1-560-124-00	PLUG, CONNECTOR (2.5MM) 4P					
V12	*1-560-123-00	PLUG, CONNECTOR (2.5MM) 3P					
V13	*1-560-127-00	PLUG, CONNECTOR (2.5MM) 7P					
CRYSTAL							
X001	1-567-162-00	OSCILLATOR, CRYSTAL					

A

(KV27XSTA only)

Num. Ref.	Num. Parte	Descrizione
-----------	------------	-------------

IC

IC101	8-759-909-08	IC TDA3541
IC102	8-759-909-54	IC TDA2546A
IC103	8-759-602-16	IC M54572L
IC151	8-759-007-54	IC TDA4940
IC152	8-759-007-55	IC TDA4944

COIL

L102	1-404-476-00	COIL, IF
L103	1-408-432-31	MICRO INDUCTOR 1.5UH
L104	1-408-406-00	MICRO INDUCTOR 5.6UH
L105	1-404-477-00	COIL, IF
L106	1-404-493-00	COIL
L107	1-404-493-00	COIL
L109	1-408-409-00	MICRO INDUCTOR 10UH
L110	1-408-406-00	MICRO INDUCTOR 5.6UH
L111	1-404-493-00	COIL
L113	1-408-226-00	MICRO INDUCTOR 82UH
L114	1-407-489-00	MICRO INDUCTOR 560UH
L115	1-408-405-00	MICRO INDUCTOR 4.7UH
L116	1-408-406-00	MICRO INDUCTOR 5.6UH
L117	1-408-428-00	MICRO INDUCTOR 390UH
L170	1-408-247-00	MICRO INDUCTOR 33MH
L171	1-408-408-00	MICRO INDUCTOR 8.2UH

TRANSISTOR

Q101	8-729-178-54	TRANSISTOR 2SC2785
Q102	8-729-105-47	TRANSISTOR 2SC2026-L
Q103	8-729-117-54	TRANSISTOR 2SA1175
Q104	8-729-900-36	TRANSISTOR DTC124ES
Q105	8-729-117-54	TRANSISTOR 2SA1175
Q151	8-729-178-54	TRANSISTOR 2SC2785
Q152	8-729-178-54	TRANSISTOR 2SC2785
Q153	8-729-178-54	TRANSISTOR 2SC2785
Q154	8-729-900-89	TRANSISTOR DTC144ES
Q155	8-729-178-54	TRANSISTOR 2SC2785
Q156	8-729-178-54	TRANSISTOR 2SC2785
Q157	8-729-900-89	TRANSISTOR DTC144ES
Q158	8-729-900-89	TRANSISTOR DTC144ES
Q172	8-729-117-54	TRANSISTOR 2SA1175
Q173	8-729-178-54	TRANSISTOR 2SC2785
Q174	8-729-178-54	TRANSISTOR 2SC2785
Q175	8-729-178-54	TRANSISTOR 2SC2785

RESISTOR

R101	1-215-738-91	METAL	1K	5%	1/6W
R102	1-215-738-91	METAL	1K	5%	1/6W
R105	1-215-762-91	METAL	10K	5%	1/6W
R106	1-215-750-91	METAL	3.3K	5%	1/6W
R107	1-215-750-91	METAL	3.3K	5%	1/6W
R108	1-215-798-91	METAL	330K	5%	1/6W
R109	1-215-746-91	METAL	2.2K	5%	1/6W

Osservazione	Num. Ref.	Num. Parte	Descrizione
--------------	-----------	------------	-------------

	R110	1-215-746-91	METAL	2.2K	5%	1/6W
	R111	1-215-754-91	METAL	4.7K	5%	1/6W
	R112	1-215-744-91	METAL	1.8K	5%	1/6W
	R113	1-215-752-91	METAL	3.9K	5%	1/6W
	R114	1-215-722-91	METAL	220	5%	1/6W
	R115	1-215-742-91	METAL	1.5K	5%	1/6W
	R116	1-215-730-91	METAL	470	5%	1/6W
	R117	1-215-710-91	METAL	68	5%	1/6W
	R118	1-215-724-91	METAL	270	5%	1/6W
	R119	1-215-730-91	METAL	470	5%	1/6W
	R120	1-215-778-91	METAL	47K	5%	1/6W
	R122	1-215-762-91	METAL	10K	5%	1/6W
	R125	1-215-736-91	METAL	820	5%	1/6W
	R126	1-215-736-91	METAL	820	5%	1/6W
	R127	1-215-736-91	METAL	820	5%	1/6W
	R131	1-215-778-91	METAL	47K	5%	1/6W
	R132	1-215-762-91	METAL	10K	5%	1/6W
	R134	1-215-782-91	METAL	68K	5%	1/6W
	R135	1-215-780-91	METAL	56K	5%	1/6W
	R136	1-215-770-91	METAL	22K	5%	1/6W
	R137	1-215-770-91	METAL	22K	5%	1/6W
	R140	1-215-738-91	METAL	1K	5%	1/6W
	R141	1-215-766-91	METAL	15K	5%	1/6W
	R142	1-215-786-91	METAL	100K	5%	1/6W
	R143	1-215-786-91	METAL	100K	5%	1/6W
	R144	1-215-752-91	METAL	3.9K	5%	1/6W
	R145	1-215-752-91	METAL	3.9K	5%	1/6W
	R146	1-215-754-91	METAL	4.7K	5%	1/6W
	R151	1-215-736-91	METAL	820	5%	1/6W
	R152	1-215-776-91	METAL	39K	5%	1/6W
	R153	1-215-728-91	METAL	390	5%	1/6W
	R154	1-215-714-91	METAL	100	5%	1/6W
	R155	1-215-770-91	METAL	22K	5%	1/6W
	R156	1-215-784-91	METAL	82K	5%	1/6W
	R157	1-215-754-91	METAL	4.7K	5%	1/6W
	R158	1-215-754-91	METAL	4.7K	5%	1/6W
	R159	1-215-754-91	METAL	4.7K	5%	1/6W
	R160	1-215-754-91	METAL	4.7K	5%	1/6W
	R161	1-215-738-91	METAL	1K	5%	1/6W
	R162	1-215-738-91	METAL	1K	5%	1/6W
	R166	1-215-750-91	METAL	3.3K	5%	1/6W
	R167	1-215-774-91	METAL	33K	5%	1/6W
	R168	1-215-770-91	METAL	22K	5%	1/6W
	R172	1-215-720-91	METAL	180	5%	1/6W
	R173	1-215-778-91	METAL	47K	5%	1/6W
	R174	1-215-796-91	METAL	270K	5%	1/6W
	R175	1-215-772-91	METAL	27K	5%	1/6W
	R176	1-215-738-91	METAL	1K	5%	1/6W
	R177	1-215-762-91	METAL	10K	5%	1/6W
	R178	1-215-762-91	METAL	10K	5%	1/6W
	R179	1-215-762-91	METAL	10K	5%	1/6W
	R180	1-215-738-91	METAL	1K	5%	1/6W
	R181	1-215-740-91	METAL	1.2K	5%	1/6W

Osservazione

Num. Ref.	Num. Parte	Descrizione
-----------	------------	-------------

R182	1-215-746-91	METAL	2.2K	5%	1/6W
R183	1-215-738-91	METAL	1K	5%	1/6W
R184	1-215-724-91	METAL	270	5%	1/6W
R185	1-215-726-91	METAL	330	5%	1/6W
R188	1-215-766-91	METAL	15K	5%	1/6W

R191	1-215-732-91	METAL	560	5%	1/6W
R192	1-215-732-91	METAL	560	5%	1/6W
R193	1-215-714-91	METAL	100	5%	1/6W

VARIABLE RESISTOR

RV101	1-228-727-00	RES, ADJ, CERAMIC CARBON 47K
RV151	1-228-726-00	RES, ADJ, CERAMIC CARBON 33K

FILTER

SWF101	1-404-438-00	FILTER, SAW
--------	--------------	-------------

TUNER

TU101A	1-463-411-21	TUNER, UHF/VHF ET (UV411/CEI)
--------	--------------	-------------------------------

KV-27XSC/27XSTC
RM-635

AEP Model

KV-27XSTC Chassis No. SCC-774D-A

Serial No. 3,004,101 and later

No. 1


SUPPLEMENT

File this supplement with the service manual

SUBJECT:MODIFICATION OF CIRCUIT

☞ : Alteration

1. SCHEMATIC DIAGRAM



2. ELECTRICAL PARTS LIST


V. BOARD

IC001 SAA5230 8-759-918-54

SAA5231 8-759-944-59

R008 METAL 56K 1-249-438-11

METAL 68K 1-249-439-11



ELECTRICAL PARTS LIST

Ref. No.	Part No.	Description	Remark	Ref. No.	Part No.	Description	Remark
*A-1135-316-A SCM BOARD, COMPLETE				TRANSISTOR			
*1-562-370-21 CONNECTOR, BOARD TO BOARD 18P				Q1351	8-729-245-B3	TRANSISTOR 2SC245B	
CAPACITOR				Q1352	8-729-204-B3	TRANSISTOR 2SA1048GR	
C1351	1-104-069-00	POLYSTYRENE 470PF	5K 50V	Q1354	8-729-245-B3	TRANSISTOR 2SC245B	
C1352	1-101-880-90	CERAMIC 47PF	5K 50V	Q1356	8-729-204-B3	TRANSISTOR 2SA1048GR	
C1353	1-110-182-81	MYLAR 0.015MF	10K 400V	Q1357	8-729-245-B3	TRANSISTOR 2SC245B	
C1354	1-123-369-00	ELECT 4.7MF	20K 25V	Q1359	8-729-245-B3	TRANSISTOR 2SC245B	
C1355	1-102-074-00	CERAMIC 0.001MF	10K 50V	Q1360	8-729-245-B3	TRANSISTOR 2SC245B	
				RESISTOR			
C1356	1-123-380-00	ELECT 1MF	20K 50V	R1351	1-215-738-91	METAL 1K 5K 1/6W	
C1357	1-102-074-00	CERAMIC 0.001MF	10K 50V	R1352	1-215-802-91	METAL 470K 5K 1/6W	
C1358	1-110-182-81	MYLAR 0.022MF	10K 250V	R1353	1-215-778-91	METAL 47K 5K 1/6W	
C1359	1-101-004-00	CERAMIC 0.01MF	50V	R1354	1-215-706-91	METAL 47 5K 1/6W	
C1360	1-101-004-00	CERAMIC 0.01MF	50V	R1355	1-215-750-91	METAL 3.3K 5K 1/6W	
C1361	1-123-332-00	ELECT 47MF	20K 16V	R1356	1-215-756-91	METAL 5.6K 5K 1/6W	
C1362	1-102-953-00	CERAMIC 18PF	5K 50V	R1357	1-215-748-91	METAL 2.7K 5K 1/6W	
C1363	1-102-953-00	CERAMIC 18PF	5K 50V	R1361	1-215-708-91	METAL 3.3K 5K 1/6W	
C1364	1-102-074-00	CERAMIC 0.001MF	10K 50V	R1364	1-215-746-91	METAL 2.7K 5K 1/6W	
C1366	1-101-006-00	CERAMIC 0.047MF	50V	R1365	1-215-762-91	METAL 10K 5K 1/6W	
C1367	1-123-356-00	ELECT 10MF	20K 16V	R1367	1-215-778-91	METAL 47K 5K 1/6W	
C1368	1-102-965-00	CERAMIC 10PF	5K 50V	R1368	1-215-738-91	METAL 1K 5K 1/6W	
C1369	1-102-824-21	CERAMIC 470PF	5K 50V	R1371	1-215-774-91	METAL 3.3K 5K 1/6W	
C1370	1-110-175-81	MYLAR 0.1MF	10K 100V	R1372	1-215-716-91	METAL 12K 5K 1/6W	
C1371	1-110-175-81	MYLAR 0.1MF	10K 100V	R1373	1-215-738-91	METAL 1K 5K 1/6W	
C1372	1-102-736-00	CERAMIC 150PF	5K 50V	R1374	1-215-746-91	METAL 2.2K 5K 1/6W	
C1373	1-101-004-00	CERAMIC 0.01MF	50V	R1375	1-215-720-91	METAL 100 5K 1/6W	
C1374	1-123-356-00	ELECT 10MF	20K 16V	R1380	1-215-770-91	METAL 27K 5K 1/6W	
C1375	1-123-318-00	ELECT 33MF	20K 16V	R1382	1-215-158-00	METAL 1.8K 5K 1/4W	
C1376	1-161-317-00	CERAMIC 330PF	10K 50V	R1383	1-215-746-91	METAL 2.2K 5K 1/6W	
C1378	1-110-182-81	MYLAR 0.022MF	10K 250V	R1384	1-215-752-91	METAL 3.9K 5K 1/6W	
DIODE				R1385	1-215-738-91	METAL 1K 5K 1/6W	
D1351	8-719-026-11	DIODE 1T261		R1386	1-215-738-91	METAL 1K 5K 1/6W	
D1355	8-719-911-19	DIODE 1SS119		R1387	1-215-200-00	METAL 100K 5K 1/4W	
IC				R1388	1-215-786-91	METAL 100K 5K 1/6W	
IC1351	8-759-922-68	IC TDA3590A-N8		R1389	1-215-734-91	METAL 680 5K 1/6W	
COIL				R1390	1-215-734-91	METAL 680 5K 1/6W	
L1351	1-404-497-00	COIL		R1393	1-215-782-91	METAL 68K 5K 1/6W	
L1352	1-404-496-00	COIL		R1394	1-215-754-91	METAL 4.7K 5K 1/6W	
L1353	1-408-408-00	MICRO INDUCTOR 8.2uH		VARIABLE RESISTOR			
L1354	1-404-498-00	COIL		RV1351	1-230-522-11	RES. ADJ. METAL GLAZE 4.7K	

KV-27XSD

RM-635

AEP Model

Serial No. 3026001 and later

Chassis No. SCC-774B-A

January, 1987


No. 1

SUPPLEMENT

SUBJECT: SCM BOARD MODIFICATION

File this supplement with the service manual.

SCHEMATIC DIAGRAM



SCM

(SCM-KILLER, Y DRIVE)
(PAL-SECAM TRANSCODER)